

TITLE OF THE INVENTION

PHOTOSENSOR SYSTEM AND DRIVE CONTROL METHOD THEREOF

CROSS-REFERENCE TO RELATED APPLICATIONS

5 This application is a continuation-in-part
application of Application 09/703,025, filed October 31,
2000.

10 This application is based upon and claims the
benefit of priority from the prior Japanese Patent
Applications No. 11-316650, filed November 8, 1999;
No. 11-319605, filed November 10, 1999; No. 2000-015981,
filed January 25, 2000, and No. 2001-198615, filed June
29, 2001, the entire contents of which are incorporated
herein by reference.

BACKGROUND OF THE INVENTION

15 The present invention relates to a photosensor
system having a photosensor array constituted by
two-dimensionally arraying a plurality of photosensors,
and a drive control method thereof.

20 Imaging apparatuses such as electronic still
cameras, video cameras, and the like have come to be
very widely used. These imaging apparatuses employ
a solid-state imaging device, such as a CCD (Charge
Coupled Device), which serves as a photoelectric
25 converting device for converting an image of a to-be-
photographed subject into an image signal. As well
known, the CCD has a structure in which photosensors
(light receiving elements) such as photodiodes, or

thin film transistors (TFT: Thin Film Transistor) are arranged in a matrix, and the amount of electron-hole pairs (the amount of charge) generated corresponding to the amount of light entering the light receiving section of each sensor is detected by a horizontal scanning circuit and vertical scanning circuit to detect the luminance of radiation.

In a photosensor system using such a CCD, it is necessary to respectively provide scanned photosensors with selective transistors for causing the scanned photosensor to assume a selected state. In place of the combination of the photosensor and the selective transistor, a photosensor (to be referred to as a double-gate photosensor hereinafter) is now being developed, which is formed of a thin film transistor having a so-called double-gate structure and has both a photosensing function and a selecting function.

FIG. 39A is a sectional view showing the structure of a double-gate photosensor 10. FIG. 39B is a circuit diagram showing the equivalent circuit of the double-gate photosensor 10.

The double-gate photosensor 10 comprises a semiconductor thin film 11 formed of amorphous silicon or the like, n^+ -silicon layers 17 and 18, source and drain electrodes 12 and 13 respectively formed on the n^+ -silicon layers 17 and 18, a top gate electrode 21 formed above the semiconductor thin film 11 via a block

insulating film 14 and upper gate insulating film 15,
a protective insulating film 20 provided on the top
gate electrode 21, and a bottom gate electrode 22
provided below the semiconductor thin film 11 via
5 a lower gate insulating film 16. The double-gate
photosensor 10 is provided on a transparent insulating
substrate 19 formed of glass or the like.

In other words, the double-gate photosensor 10
includes an upper MOS transistor comprised of the
10 semiconductor thin film 11, source electrode 12, drain
electrode 13, and top gate electrode 21, and a lower
MOS transistor comprised of the semiconductor thin film
11, source electrode 12, drain electrode 13, and bottom
gate electrode 22. As shown in the equivalent circuit
15 of FIG. 31B, the double-gate photosensor 10
is considered to include two MOS transistors having
a common channel region formed of the semiconductor
thin film 11, TG (Top Gate terminal), BG (Bottom Gate
terminal), S (Source terminal), and D (drain Terminal).

20 The protective insulating film 20, top gate
electrode 21, upper gate insulating film 15, block
insulating film 14, and lower gate insulating film
16 are all formed of a material having a high
transmittance of visible light for activating the
25 semiconductor thin film 11. Light entering the sensor
from the top gate electrode 21 side passes through the
top gate electrode 21, upper gate insulating film 15,

and block insulating film 14, and then enters the semiconductor thin film 11, thereby generating and accumulating charges (positive holes) in the channel region.

5 FIG. 40 is a schematic view showing a photosensor system constituted by two-dimensionally arraying double-gate photosensors 10. As shown in FIG. 40, the photosensor system comprises a sensor array 100 that is constituted of a large number of double-gate
10 photosensors 10 arranged in an $n \times m$ matrix, top and bottom gate lines 101 and 102 that respectively connect the top gate terminals TG and bottom gate terminals BG of the double-gate photosensors 10 in a row direction, top and bottom gate drivers 111 and 112 respectively
15 connected to the top and bottom gate lines 101 and 102, data lines 103 that respectively connect the drain terminals D of the double-gate photosensors 10 in a column direction, and an output circuit section 113 connected to the data lines 103.

20 In FIG. 40, ϕ_{tg} and ϕ_{bg} represent control signals for generating a reset pulse ϕ_{Ti} and readout pulse ϕ_{Bi} , respectively, which will be described later, and ϕ_{pg} represents a pre-charge pulse for controlling the timing at which a pre-charge voltage V_{pg} is applied.

25 In the above-described structure, as described later, the photosensing function is realized by applying a predetermined voltage from the top gate

driver 111 to the top gate terminals TG, while the readout function is realized by applying a predetermined voltage from the bottom gate driver 112 to the bottom gate terminals BG, then sending the output voltage of the photosensors 10 to the output circuit section 113 via the data lines 103, and outputting serial data Vout.

FIGS. 41A to 41D are timing charts showing a method of controlling the photosensor system, and showing a detecting period (i-th row processing cycle) in the i-th row of the sensor array 100. First, a high-level pulse voltage (reset pulse; e.g., $V_{tg} = +15V$) ϕ_{Ti} shown in FIG. 41A is applied to the top gate line 101 of the i-th row, and during a reset period T_{reset} , reset operation for discharging the double-gate photosensors 10 of the i-th row is executed.

Subsequently, a bias voltage ϕ_{Ti} of low level (e.g., $V_{tg} = -15V$) is applied to the top gate line 101 of the i-th row, thereby finishing the reset period T_{reset} and starting a charge accumulating period T_a in which the channel region is charged. During the charge accumulating period T_a , charges (positive holes) corresponding to the amount of light entering each sensor from the top gate electrode side are accumulated in the channel region.

Then, a pre-charge pulse ϕ_{pg} shown in FIG. 41C with a pre-charge voltage V_{pg} is applied to the data

lines 103 during the charge accumulating period T_a , and after a pre-charge period T_{prch} for making the drain electrodes 13 keep a charge, a bias voltage (readout pulse ϕ_{Bi}) of high level (e.g., $V_{bg} = +10V$) shown in FIG. 41B is applied to the bottom gate line 102 of the i -th row. At this time, the double-gate photosensors 10 of the i -th row are turned on to start a readout period T_{read} .

During the readout period T_{read} , the charges accumulated in the channel region serve to moderate a low-level voltage (e.g., $V_{tg} = -15V$) which has an opposite polarity of charges accumulated in the channel region and is applied to each top gate terminal TG. Therefore, an n-type channel is formed by the voltage V_{bg} at each bottom gate terminal BG, the voltage V_D at the data lines 103 gradually reduces in accordance with the drain current with lapse of time after the pre-charge voltage V_{pg} is applied. More specifically, the tendency of change in the voltage V_D at the data lines 103 depends upon the amount of received light in the case where the charge accumulating period T_a is constant. As shown in FIG. 41D, the voltage V_D tends to gradually reduce when the incident light is dark, i.e., a small amount of light is received, and hence only small charges are accumulated, whereas the voltage V_D tends to suddenly reduce when the incident light is bright, i.e., a large amount of light is received, and

hence large charges are accumulated. From this, it is understood that the amount of radiation can be calculated by detecting the voltage V_D at the data lines 103 a predetermined period after the start of the readout period T_{read} , or by detecting a period required until the voltage V_D reaches a predetermined threshold voltage. An image reading sensitivity corresponds to the charge accumulating period T_a . Assuming that the amount of light is constant, the amount of charge accumulated increases and the image reading sensitivity enhanced in accordance with an increase in the charge accumulating period T_a . Likewise, the amount of charge accumulated decreases and the image reading sensitivity degraded in accordance with a decrease in the charge accumulating period T_a .

Image reading is performed by sequentially executing the above-described drive-control for each line of the sensor array 100, by executing the control for each line in a parallel manner at different timings at which the driving pulses do not overlap.

Although the case of using the double-gate photosensor as a photosensor has been described above, even a photosensor system using a photodiode or phototransistor as a photosensor has operation steps: reset operation \rightarrow charge accumulating operation \rightarrow pre-charge operation \rightarrow reading operation, and uses a similar drive sequence. The conventional photosensor

system as above has the following problems.

(1) To read a subject image in various use environments in a photosensor system using the above-described photosensor, the image reading sensitivity (charge accumulating period) must be properly set. The proper image reading sensitivity changes depending on changes in ambient conditions such as the illuminance of external light in a use environment, and also changes when the characteristics of the photosensor change. In the prior art, therefore, a circuit for detecting the illuminance of external light must be additionally arranged. Alternatively, a subject image is read at different image reading sensitivities before the start of normal reading operation of that subject image, and an optimal image reading sensitivity must be determined on the basis of a read result. However, a reading sensitivity setting method of unconditionally and automatically setting a proper image reading sensitivity based on a read result for every image reading sensitivity that is obtained by operations executed at different image reading sensitivities, has not been developed yet.

(2) If a foreign substance attaches to the sensing surface of a photosensor or a defect is generated in a photosensor element in setting the reading sensitivity based on the result of the sensitivity-adjusting reading operation, and a read result obtained for each

image reading sensitivity obtained in the reading operation is directly used, an abnormal value is contained in the read result, leading to failure to set a proper image reading sensitivity and to inhibit accurate reading operation of a subject image. For example, when this photosensor system is applied to a fingerprint reading apparatus, the apparatus may malfunction in fingerprint recognition processing.

BRIEF SUMMARY OF THE INVENTION

It is an object of the present invention to provide a reading sensitivity setting method of unconditionally and automatically setting a proper image reading sensitivity in order to accurately read a subject image in various use environments in a photosensor system. The present invention is advantageous in that any malfunction in setting the image reading sensitivity is prevented even if a foreign substance attaches to the sensing surface of a photosensor, or a photosensor element becomes defective.

To achieve the above advantage, a photosensor system according to the present invention comprises: a photosensor array constituted by two-dimensionally arranging a plurality of photosensors; an image reader which read a subject image by use of the photosensor array; a sensitivity-adjusting reader which read the subject image while changing the image reading

sensitivity of the photosensor array stepwise; optimal
image reading sensitivity extracting means for
extracting an optimal image reading sensitivity
suitable for the image reading operation on the basis
5 of a predetermined measurement amount relating to an
image pattern of the subject image read by the
sensitivity-adjusting reader; and reading sensitivity-
setting means for setting the optimal image reading
sensitivity to a reading sensitivity of the image
10 reader.

According to the first reading sensitivity setting
method of the present invention, the sensitivity-
adjusting reader executes sensitivity-adjusting reading
operation at a plurality of stages for, e.g.,
15 respective rows. The optimal image reading
sensitivity-extracting means extracts an image reading
sensitivity that allows the dynamic range of the
measurement amount of each row to become maximal, on
the basis of the predetermined measurement amount
20 regarding the image pattern of the subject image.
Alternatively, the optimal image reading sensitivity-
extracting means extract a row in which the dynamic
range becomes maximal and a displacement of the dynamic
range between image reading sensitivity becomes
25 minimal. The row is extracted in accordance with the
dynamic range that is determined for each image reading
sensitivity after high-frequency components

corresponding to a change in the dynamic range of the measurement amount of each row have been removed. The reading sensitivity-setting means sets the image reading sensitivity corresponding to the extracted row as an optimal sensitivity. This can reduce the amount of data subjected to the extraction processing of the optimal image reading sensitivity, simplify sensitivity setting processing, and shorten the required time. Even when the ambient light or the characteristics of the photosensor change, an optimal image reading sensitivity can be set in accordance with the changes. In addition, a suitable image reading sensitivity can be extracted without being adversely affected by a foreign substance attached to the sensing surface of the photosensor array, an abnormal pixel due to a defective element included in the photosensor element, or the like.

According to the second reading sensitivity setting method of the present invention, the sensitivity-adjusting reader changes the image reading sensitivity stepwise with respect to the photosensors of a specific row section of the photosensor array, and sensitivity-adjusting reading operation is performed by reading a subject image portion corresponding to the specific row section. Owing to this, the time needed for the sensitivity-adjusting reading operation can be as short as possible. In addition, the amount of data

used for the extraction of an optimal image reading sensitivity can be significantly reduced, thereby shortening the processing time.

5 In this case, abnormal pixel determining element
is provided for determining whether or not any abnormal
pixel exists in a specific row section by checking if
the measurement amount pertaining to the specific row
section and corresponding to each column changes when
the image reading sensitivity is switched from one to
10 another. Sensitivity-adjusting read controlling means
is also provided for executing sensitivity-adjusting
reading operation for a specific row section other than
the specific row section where the abnormal pixel is
determined to exist. With this structure, even if an
15 abnormal pixel exists in the specific row section for
which the sensitivity-adjusting reading operation is
performed, another specific row section is selected to
avoid the adverse effects the abnormal pixel may have.

Additional objects and advantages of the invention
20 will be set forth in the description which follows, and
in part will be obvious from the description, or may
be learned by practice of the invention. The objects
and advantages of the invention may be realized and
obtained by means of the instrumentalities and combina-
25 tions particularly pointed out hereinafter.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated

in and constitute a part of the specification, illustrate presently preferred embodiments of the invention, and together with the general description given above and the detailed description of the preferred embodiments given below, serve to explain the principles of the invention.

FIG. 1 is a block diagram showing an arrangement of a photosensor system according to the present invention;

FIG. 2 is a block diagram showing an arrangement of a controller applied to the first embodiment;

FIG. 3 is a flow chart showing operation of the first embodiment;

FIG. 4 is a view showing an example of image data when a fingerprint image is read by sensitivity-adjusting reading operation in the first embodiment;

FIGS. 5A to 5E are graphs each showing changes in lightness data in a specific row that are obtained by sensitivity-adjusting reading operation in the first embodiment;

FIGS. 6A and 6B are views showing the relationship between a table representing the dynamic range of lightness data of each row that is obtained by sensitivity-adjusting reading operation in the first embodiment, and a corresponding row number vs. image reading sensitivity correspondence table;

FIG. 7 is a view showing another example of image

data when a fingerprint image is read by sensitivity-adjusting reading operation in a modification of the first embodiment;

5 FIGS. 8A to 8E are graphs each showing changes in lightness data in the column range of a specific region in a specific row that are obtained by sensitivity-adjusting reading operation in the modification of the first embodiment;

10 FIGS. 9A and 9B are tables showing the relationship between a table representing the dynamic range of lightness data of each row that is obtained by sensitivity-adjusting reading operation in the modification of the first embodiment, and a corresponding row number vs. image reading sensitivity
15 correspondence table;

FIG. 10 is a flow chart showing operation of the second embodiment;

FIG. 11 is a view showing an example of image data when a fingerprint image is read by sensitivity-adjusting reading operation in the second embodiment;
20

FIGS. 12A and 12B are graphs, respectively, showing the value of lightness data in a predetermined column that is obtained by sensitivity-adjusting reading operation in the second embodiment, and the
25 differentiated value of lightness data between rows;

FIGS. 13A and 13B are views showing the relationship between a table representing the differentiated

value of lightness data between rows in a predetermined column that is obtained by sensitivity-adjusting reading operation in the second embodiment, and a corresponding row number vs. image reading sensitivity correspondence table;

FIG. 14 is a flow chart showing operation of the third embodiment;

FIG. 15 is a view showing examples of image data and a sensitivity determination range when a fingerprint image is read by sensitivity-adjusting reading operation in the third embodiment;

FIG. 16 is a graph showing changes in lightness data of a specific row in the sensitivity determination range of image data read by sensitivity-adjusting reading operation in the third embodiment;

FIGS. 17A and 17B are graphs showing the relationship between changes in the dynamic ranges of respective rows of image data read by sensitivity-adjusting reading operation in the third embodiment, and changes in the linearly differentiated values of the dynamic ranges of respective rows;

FIGS. 18A and 18B are views showing the relationship between a table representing the dynamic range of each row and the linearly differentiated value of the dynamic range that are obtained by sensitivity-adjusting reading operation in the third embodiment, and a corresponding row number vs. image reading

sensitivity correspondence table;

FIGS. 19A and 19B are views showing the relationship between a table representing the dynamic range of each row and a corresponding row number vs. image reading sensitivity correspondence table when the first embodiment is applied to image data read by sensitivity-adjusting reading operation in the third embodiment;

FIG. 20 is a view showing a case wherein an abnormal value exists in read image data of a fingerprint image in sensitivity-adjusting reading operation in the third embodiment;

FIG. 21 is a graph showing changes in the dynamic ranges of respective rows when an abnormal value exists in read image data of a fingerprint image in sensitivity-adjusting reading operation in the third embodiment;

FIGS. 22A and 22B are graphs showing the relationship between changes in the dynamic ranges of respective rows, and changes in the linearly differentiated values of the dynamic ranges of respective rows when an abnormal value exists in read image data of a fingerprint image in sensitivity-adjusting reading operation in the third embodiment;

FIG. 23 is a flow chart showing operation of the fourth embodiment;

FIG. 24 is a block diagram showing an arrangement

of a controller applied to the fifth embodiment;

FIG. 25 is a flow chart showing operation of the fifth embodiment;

5 FIG. 26 is a view showing a case wherein an abnormal value across a plurality of rows exists in read image data of a fingerprint image in sensitivity-adjusting reading operation of the fifth embodiment;

10 FIG. 27A is a graph showing changes in the dynamic ranges of respective rows when an abnormal value across a plurality of rows exists in read image data of a fingerprint image in sensitivity-adjusting reading operation of the fifth embodiment, and the dynamic range discretely varies for respective rows;

15 FIG. 27B is a graph showing the dynamic range distribution of lightness data of respective rows after abnormal value removing operation in the fifth embodiment;

FIG. 28 is a flowchart illustrating operation of the sixth embodiment;

20 FIG. 29 shows a specific row section of a photosensor array for which sensitivity-adjusting reading operation is performed according to the sixth embodiment, the specific row section being illustrated in relation to a subject image;

25 FIGS. 30A to 30E are graphs showing how lightness data on a specific row section changes in the sixth embodiment, in relation to the number of times the

reading operation is performed;

FIG. 31 is a graph showing how a dynamic range changes in the sixth embodiment, in relation to the number of times the reading operation is performed;

5 FIG. 32 is a flowchart illustrating operation of the seventh embodiment;

FIG. 33 shows a specific row section of a photosensor array for which sensitivity-adjusting reading operation is performed according to the seventh
10 embodiment, the specific row section being illustrated in relation to a subject image;

FIGS. 34A to 34E are graphs showing how lightness data on a specific row section changes in the seventh
15 embodiment, in relation to the number of times the reading operation is performed; FIGS. 35A to 35J are timing charts showing the first embodiment of an image reading sensitivity setting method applied to sensitivity-adjusting reading operation executed in each of the first to fifth embodiments;

20 FIGS. 36A to 36J. are timing charts showing the second embodiment of an image reading sensitivity setting method applied to sensitivity-adjusting reading operation executed in each of the first to fifth embodiments;

25 FIGS. 37A to 37L are timing charts illustrating an image reading sensitivity-setting method that is applicable to the sensitivity-adjusting reading

operation executed according to the sixth and seventh embodiments;

5 FIGS. 38A to 38H are timing charts showing an embodiment when an effective voltage adjusting period is set after sensitivity-adjusting reading operation and image reading periods in a photosensor system drive control method according to the present invention;

 FIG. 39A is a sectional view showing the structure of a conventional double-gate photosensor;

10 FIG. 39B is an equivalent circuit diagram showing the double-gate photosensor;

 FIG. 40 is a schematic view showing a photosensor system constituted by two-dimensionally arraying double-gate photosensors; and

15 FIGS. 41A to 41D are timing charts showing a conventional drive method for the double-gate photosensor system.

DETAILED DESCRIPTION OF THE INVENTION

20 Methods of controlling a photosensor system according to the present invention will be described in detail with reference to the several views of the accompanying drawings. Although in embodiments described below, a double-gate photosensor is applied as a photosensor, the present invention is not limited
25 to the double-gate photosensor, but is also applicable to a photosensor system using another type of photosensor.

FIG. 1 is a block diagram showing an arrangement of a photosensor system according to the present invention. The double-gate photosensor shown in FIG. 39A is used, and the arrangement of the
5 photosensor system shown in FIG. 40 will be referred to if necessary. The same reference numerals as in the photosensor system shown in FIG. 40 denote the same parts.

As shown in FIG. 1, the photosensor system
10 according to an embodiment comprises a photosensor array 100 including double-gate photosensors 10 shown in FIG. 39A that are arrayed two-dimensionally, a top gate driver 111 for applying a predetermined reset pulse to a top gate terminal TG of each double-gate
15 photosensor 10 at a predetermined timing, a bottom gate driver 112 for applying a predetermined readout pulse to a bottom gate terminal BG of each double-gate photosensor 10 at a predetermined timing, an output circuit section 113 constituted by an amplifier 116,
20 and a column switch 114 and pre-charge switch 115 for reading a data line voltage and applying a pre-charge voltage to each double-gate photosensor 10, respectively, an analog/digital converter (to be referred to as an A/D converter hereinafter) 117 for converting the
25 read data voltage as an analog signal into image data as a digital signal, a controller 120 which is adopted to control the operation of reading a subject image by

the photosensor array 100, and to exchange data with an external function section 200, and which controls sensitivity setting in the present invention, and a RAM 130 that stores, for example, read image data, data relating to setting of a reading sensitivity described later.

The structure including the photosensor array 100, top gate driver 111, bottom gate driver 112, and output circuit section 113 is the same as and has the same function as the photosensor system shown in FIG. 40. In addition to this structure, this embodiment adopts the A/D converter 117, controller 120, and RAM 130 to enable various types of control as described below.

The controller 120 outputs control signals ϕ_{tg} and ϕ_{bg} to the top and bottom gate drivers 111 and 112, respectively, which, in turn, output predetermined voltages (reset pulse and readout pulse) to the top gate terminal TG and bottom gate terminal BG of each double-gate photosensor 10 of the photosensor array 100, respectively. The controller 120 also outputs a control signal ϕ_{pg} to the pre-charge switch 115 to control execution of the operation of reading a subject image. A data line voltage read from the photosensor array 100 via the column switch 114 and amplifier 116 is converted into a digital signal by the A/D converter 117, and supplied as image data. The controller 120 also has a function of executing predetermined image

processing for image data, writing or reading image data into or from the RAM 130. The controller 120 serves as an interface with the external function section 200 that executes predetermined processing such as image data identification, modification, and the like.

The controller 120 has another function of controlling control signals to be output to the top and bottom gate drivers 111 and 112 to set an optimal reading sensitivity for reading a subject image in accordance with ambient environments such as the illuminance of external light, i.e., an optimal charge accumulating period for each double-gate photosensor 10.

As will be described below, photosensor system drive control methods according to embodiments of the present invention are based on the arrangement of this photosensor system.

<First Embodiment>

The first embodiment of the photosensor system drive control method according to the present invention will be described with reference to the several views of the accompanying drawing.

FIG. 2 is a block diagram showing an arrangement of a controller 120 applied to the first embodiment. As shown in FIG. 2, the controller 120 comprises a device controller 121 for controlling a top gate driver

111, bottom gate driver 112, and output circuit section 113, a data controller 122 for managing various data such as image data, write data, and readout data to the RAM 130, and a main controller 123 which supervises the controllers 121 and 122 and interfaces with an external function section.

The controller 120 further comprises a data comparator 124 for comparing the sizes of specific measurement data based on image data input as a digital signal from a photosensor array 100 via an A/D converter 117 to extract maximum and minimum values, an adder 125 having a function of calculating, e.g., the difference between measurement data, a data selector 126 for receiving processed image data via the A/D converter 117, data comparator 124, and adder 125, and switching write/readout in/from the RAM, re-input to the data comparator 124 and adder 125, and output to the external function section via the data controller 122 in accordance with the received data, and a sensitivity setting register 127 for changing control signals to be output from the device controller 121 to the top and bottom gate drivers 111 and 112 so as to optimize the reading sensitivity of the photosensor array on the basis of a control signal from the data controller 122.

The operation of the first embodiment in the operation control method of the photosensor system

using the above controller 120 will be explained with reference to FIG. 3. FIG. 3 is a flow chart showing an operation up to read of a subject image with an optimal sensitivity according to the first embodiment in operation control of the photosensor system. This operation will be described by properly referring to the arrangement of the photosensor system shown in FIGS. 1 and 2.

In S11 (sensitivity-adjusting reading operation) of FIG. 3, the main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in the sensitivity setting register 127 via the data controller 122, and executes sensitivity-adjusting reading operation for a subject image. These operations are executed prior to normal reading operation of a subject image, for example. Similar to normal image reading operation, the sensitivity-adjusting reading operation is done by executing a series of processes: reset operation → charge accumulating operation → pre-charge operation → readout operation. In the pre-reading operation, the image reading sensitivity is changed stepwise for, e.g., respective rows of a subject image so as to read one subject image at a plurality of different sensitivities. The image reading sensitivities of respective rows are stored in the RAM 130 in, e.g., a table format (row number vs. image reading sensitivity

correspondence table) in correspondence with row numbers. A detailed image reading sensitivity setting method will be described later.

5 In S12 (image data conversion step) of FIG. 3, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via the amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to the data comparator 124. In
10 this case, the lightness data is expressed by, e.g., 256 gray levels.

In S13 (step of extracting the maximum and minimum values of each row) of FIG. 3, the data comparator 124 extracts the maximum and minimum values of each row from the lightness data input to the data comparator
15 124, and outputs them to the adder 125. That is, the data comparator 124 extracts lightness data representing a maximum value (gray level value of the brightest pixel) contained in each row, and lightness data
20 representing a minimum value (gray level value of the darkest pixel).

In S14 (step of calculating the dynamic range of each row) of FIG. 3, the adder 125 calculates as a dynamic range the difference between the maximum and
25 minimum values of lightness data of each row, and stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range

calculation processing for all the rows.

In S15 (step of extracting a row number having a maximum dynamic range) of FIG. 3, the dynamic ranges of respective rows stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number having the maximum dynamic range among the dynamic ranges of the respective rows.

In S16 (sensitivity referring/extraction step) of FIG. 3, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is looked up based on the row number having the maximum dynamic range, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

In S17 (extracted sensitivity setting step) of FIG. 3, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity.

In S18 (subject image reading step) of FIG. 3, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the first embodiment of the photosensor system drive control method using the above-described controller 120 to a fingerprint reading apparatus will be described with reference to FIGS. 4

to 6B.

FIG. 4 is a view showing an example of fingerprint image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIGS. 5A to 5E are graphs each showing changes in lightness data in several rows that are based on the subject image data obtained by the sensitivity-adjusting reading operation. FIGS. 6A and 6B are views for illustrating tables showing the relationship between the dynamic range of lightness data of each row that is obtained by pre-reading operation, and a row number vs. image reading sensitivity correspondence table. Assume that image data is read out in units of a matrix pattern of 256 rows \times 196 columns. A larger lightness data value represents a brighter image, and a smaller lightness data value represents a darker image. In the sensitivity-adjusting reading operation, the image reading sensitivity is set higher (charge accumulating period is set longer) for a larger row number (upward in FIG. 4), and lower (charge accumulating period is set shorter) for a smaller row number (downward in FIG. 4). In FIG. 4, as the row number increases (upward in FIG. 4), the ridge/valley pattern of the fingerprint becomes weaker under the influence of external light, and at last is read as an almost

invisibly bright image. On the other hand, as the row number decreases (downward in FIG. 4), the ridge/valley pattern of the fingerprint becomes darker, and at last is read as an almost invisibly dark image. The lightness data level is expressed by 256 gray levels, and its lower and upper limit values are set to 0 and 255, respectively.

In this image data, changes in lightness data in the 176th, 152nd, 128th, 104th, and 80th rows are extracted, and plotted as shown in FIGS. 5A to 5E. In the 176th row, as shown in FIG. 5A, the sensitivity is set high, so that lightness data substantially converges to the upper limit value and hardly provides any information as image data. In the 152nd row, as shown in FIG. 5B, the sensitivity is set relatively high, lightness data reaches the upper limit value in some columns, and all the ridge/valley (bright/dark) patterns of image data cannot be read. To the contrary, in the 128th row, as shown in FIG. 5C, lightness data does not reach either the upper or lower limit value on all the columns, and is distributed between the upper and lower limit values. In the 104th row, as shown in FIG. 5D, the sensitivity is set relatively low, and most of lightness data is distributed between the upper and lower limit values. However, lightness data reaches the lower limit value on some columns, and all the ridge/valley patterns of

image data cannot be read. In the 80th row, as shown in FIG. 5E, the sensitivity is set low, so that lightness data substantially converges to the lower limit value and hardly provides any information as image data.

Maximum and minimum values are extracted as numerical data on the basis of changes in the lightness data distribution of each of the respective rows shown in FIGS. 5A to 5E, and the dynamic range is calculated as the difference and listed on a table as shown in FIG. 6A. In the 176th and 152nd rows, lightness data reaches the upper limit. Since the maximum value is fixed to 255, the dynamic range depends on the minimum value. In the 104th and 80th rows, lightness data reaches the lower limit. Since the minimum value is fixed to 0, the dynamic range depends on the maximum value. In contrast, in the 128th row, lightness data does not reach either the upper or lower limit, and thus the dynamic range depends on the difference between the maximum and minimum values of the lightness data. The 128th row can attain the largest dynamic range, compared to the 176th, 152nd, 104th, and 80th rows. In other words, it can be determined that lightness data in the 128th row is image data having a fine contrast corresponding to the ridge/valley pattern of a fingerprint, and an optimal image reading sensitivity is set.

The RAM 130 stores the row number vs. image reading sensitivity correspondence table shown in FIG. 6B, and stores image reading sensitivities, i.e., charge accumulating periods T_1 to T_{256} for respective row numbers.

The row number vs. image reading sensitivity correspondence table is looked up for the 128th row having the maximum dynamic range, thereby obtaining an image reading sensitivity, i.e., charge accumulating period T_{128} set for the 128th row.

If a subject (fingerprint) image is read using the obtained charge accumulating period T_{128} , the image can be satisfactorily read.

The first embodiment has exemplified only the 176th, 152nd, 128th, 104th, and 80th rows as rows subjected to extraction and calculation processes of the dynamic range of lightness data. As a matter of course, the same processes can be executed for all 256 rows. When extraction and calculation processes of the dynamic range of lightness data are performed not for all the rows but for only selected specific rows, like this embodiment, the number of data to be processed can be decreased to simplify processing and shorten the time required for sensitivity setting processing, and the operation can quickly shift to normal reading operation of a subject image.

A modification of the first embodiment will be

described with reference to FIGS. 7, 8A to 8E, 9A,
and 9B. FIG. 7 is a view showing another example of
fingerprint image data when a subject (fingerprint)
image is read while the image reading sensitivity is
5 changed stepwise for respective rows in sensitivity-
adjusting reading operation. FIGS. 8A to 8E are graphs
each showing changes in lightness data in the column
range of a specific region in several rows that are
based on the subject image data obtained by the
10 sensitivity-adjusting reading operation. FIGS. 9A and
9B are tables showing the relationship between the
dynamic range of lightness data of each row that is
obtained by the sensitivity-adjusting reading
operation, and a row number vs. image reading
15 sensitivity correspondence table. In this
modification, unlike the first embodiment, lightness
data of each row used to extract maximum and minimum
values is limited to the column range of a specific
region, and maximum and minimum values in this column
20 range are extracted.

More specifically, in reading the ridge/valley
pattern of a fingerprint as a subject image, the
peripheral portion of a finger (region representing
the edge of a finger in FIG. 7) touches an image
25 reading surface weaker than the center of the finger.
In addition, the ridge/valley pattern of the peripheral
portion is not clear, and is influenced by external

factors such as external light incident via the semitransparent layer of a skin surface layer. This degrades the uniformity and relevance of image data. To prevent this, the modification processes lightness data limited to a column range around the center of a finger which is relatively hardly influenced by external factors and has a clear ridge/valley pattern, thereby achieving appropriate extraction processing of maximum and minimum values.

As shown in FIG. 7, the reading sensitivity of a subject image is set higher (charge accumulating period is set longer) for a larger row number. For example, changes in lightness data in a predetermined column range (85th column to 112th column) in the 176th, 152nd, 128th, 104th, and 80th rows are extracted and plotted as shown in FIGS. 8A to 8E. Similar to FIGS. 5A to 5E described above, only in the 128th row, lightness data does not reach either the upper or lower limit value in the entire column range partially limited, and is distributed between the upper and lower limit values. In the remaining rows, lightness data reaches the upper or lower limit value, and all the ridge/valley patterns of image data cannot be read.

FIG. 9A shows the results of extracting maximum and minimum values as numerical data on the basis of changes in lightness data distribution of each row, and calculating the dynamic range from the difference.

It can be determined that the dynamic range of lightness data in the 128th row is maximum, and that image data having a fine contrast corresponding to the ridge/valley pattern of a fingerprint is obtained.

5 That is, an optimal image reading sensitivity can be determined to be set.

As shown in FIG. 6B, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 stores charge accumulating periods T_1 to T_{256} for respective row numbers. As shown in FIG. 9B, the row number vs. image reading sensitivity correspondence table is looked up for the 128th row having the maximum dynamic range, thereby attaining an image reading sensitivity set for the 128th row, i.e., charge accumulating period T_{128} of the double-gate photosensor.

The sensitivity setting method of this modification can determine a row in an optimal image reading state on the basis of the dynamic range of lightness data in a predetermined column range for each row in setting an optimal image reading sensitivity based on the results of sensitivity-adjusting reading operation. Accordingly, the data amount to be processed can be decreased to simplify sensitivity setting processing and shorten the required time.

<Second Embodiment>

The second embodiment of a photosensor system

drive control method to which the same controller 120 as in the first embodiment can be applied will be described with reference to the several views of the accompanying drawing.

5 FIG. 10 is a flow chart showing an operation up to read of a subject image with an optimal sensitivity according to the second embodiment in operation control of the photosensor system. This operation will be described by properly referring to the arrangement of
10 the photosensor system shown in FIGS. 1 and 2.

 In S21 (sensitivity-adjusting reading operation) of FIG. 10, a main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in a sensitivity setting register 127
15 via a data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise for respective rows of the subject image. These
20 operations are executed prior to normal reading operation of a subject image, for example. The image reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspondence table in a RAM 130 in correspondence with row
25 numbers. This sensitivity-adjusting reading operation is the same as the operation in the first embodiment, and a detailed method of setting the image reading

sensitivity (charge accumulating period) will be described below.

5 In S22 (image data conversion step) of FIG. 10, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via an amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to a data comparator 124. In this case, the lightness data is expressed by, e.g.,
10 256 gray levels.

In S23 (data extraction step in the column direction) of FIG. 10, the data comparator 124 extracts lightness data on a specific column, and outputs it to an adder 125.

15 In S24 (differentiation processing step in the column direction) of FIG. 10, the adder 125 calculates the displacement (differentiated value) of each row in the column direction of the extracted luminance data, and stores the displacement in the RAM 130.

20 In S25 (step of extracting a row number having the maximum differentiated value) of FIG. 10, the differentiated values of lightness data stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row
25 number having the maximum differentiated value among the differentiated values of lightness data.

In S26 (sensitivity referring/extraction step) of

FIG. 10, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is referred based on the row number having the maximum differentiated value, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

In S27 (extracted sensitivity setting step) of FIG. 10, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity. In S28 (subject image reading step) of FIG. 10, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the second embodiment of the photosensor system drive control method to a fingerprint reading apparatus will be described with reference to FIGS. 11 to 13B.

FIG. 11 is a view showing an example of fingerprint image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIGS. 12A and 12B are graphs, respectively, showing the value of lightness data in a predetermined column that is obtained by the sensitivity-adjusting reading operation, and the

displacement (differentiated value) of lightness data between rows. FIGS. 13A and 13B are tables showing the relationship between the displacement of lightness data between rows in a predetermined column that is obtained by the sensitivity-adjusting reading operation, and a row number vs. image reading sensitivity correspondence table. Assume that image data is read out in units of a matrix pattern of 256 rows \times 196 columns. A larger lightness data value represents a brighter image, and a smaller lightness data value represents a darker image.

In the sensitivity-adjusting reading operation, the image reading sensitivity is set higher (charge accumulating period is set longer) for a larger row number (upward in FIG. 11), and lower (charge accumulating period is set shorter) for a smaller row number (downward in FIG. 11). For example, lightness data of respective rows (1st to 256th rows) on the 98th column are extracted and plotted as shown in FIG. 12A.

In a region having a small row number, the image reading sensitivity is set low, and lightness data converges to the lower limit value. In a region having a large row number, the image reading sensitivity is set high, and lightness data converges to the upper limit value. To the contrary, in a region around the central row (128th row), lightness data does not reach either the upper or lower limit value, and is

distributed between the upper and lower limit values. Further, lightness data tends to change from the lower limit value to the upper limit value.

Differentiated values representing the
5 displacements of lightness data of respective rows are
calculated based on changes in lightness data of these
rows, and plotted to obtain a distribution as shown in
FIG. 12B. The distribution of the differentiated value
of lightness data shown in FIG. 12B is listed on
10 a table as shown in FIG. 13A. From this table, the
differentiated value is observed to maximize between
the 125th and 126th rows, and image data having a fine
contrast corresponding to the ridge/valley pattern of
the fingerprint is determined to be obtained. That is,
15 an optimal image reading sensitivity can be determined
to be set.

Similar to the table shown in FIG. 6B, the row
number vs. image reading sensitivity correspondence
table stored in the RAM 130 stores charge accumulating
20 periods T_1 to T_{256} for respective row numbers. This
table is looked up for the 125th and 126th rows having
the maximum differentiated value to acquire image
reading sensitivities set for the 125th and 126th rows,
i.e., charge accumulating periods T_{125} and T_{126} of the
25 photosensor. The sensitivity setting register is
rewritten to set a set value determined based on the
two charge accumulating periods T_{125} and T_{126} , i.e.,

the average of the charge accumulating periods T_{125} and T_{126} . A subject (fingerprint) image is read at this optimal image reading sensitivity.

5 Similar to the modification of the first
embodiment, the column number of lightness data to be
processed is desirably specified to a column around
the central portion of a subject (finger) which is
relatively hardly influenced by external factors and at
which the bright/dark pattern (ridge/valley pattern) of
10 a subject image can be read clearly.

 In setting an optimal image reading sensitivity
based on the results of sensitivity-adjusting reading
operation, the sensitivity setting method of the second
embodiment can easily determine a row in an optimal
15 image reading state on the basis of the displacement of
lightness data of each row in a specific column, and
can set an image reading sensitivity (charge
accumulating period) set for this row as an optimal
sensitivity. Lightness data to be processed suffices
20 to be one column (i.e., several rows), and data to be
processed in sensitivity setting processing can be
greatly decreased to further simplify sensitivity
setting processing and shorten the required time.
<Third Embodiment>

25 The third embodiment of a photosensor system drive
control method according to the present invention will
be described with reference to the several views of the

accompanying drawings.

The arrangement of a controller applied to the third embodiment has the same arrangement block as the controller 120 employed in the first and second
5 embodiments shown in FIG. 2. In addition, an adder 125 calculates a dynamic range from the difference between the maximum and minimum values of measurement data, and calculates the difference between respective dynamic ranges, i.e., linearly differentiated value. A data
10 comparator 124 has a function of extracting the maximum value of a dynamic range calculated by the adder 125, and the minimum or maximum value of the difference (linearly differentiated value) between dynamic ranges.

FIG. 14 is a flow chart showing an operation up
15 to read of a subject image with an optimal sensitivity according to the third embodiment in the photosensor system operation control method using the above controller 120. This operation will be described by properly referring to the arrangement of the
20 photosensor system shown in FIGS. 1 and 2.

In S31 (sensitivity-adjusting reading operation) of FIG. 14, a main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in a sensitivity setting register 127
25 via a data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities

while changing the image reading sensitivity stepwise for respective rows of the subject image. These operations are executed prior to normal reading operation of a subject image, for example. The image reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspondence table in a RAM 130 in correspondence with row numbers. This sensitivity-adjusting reading operation is the same as the operation in the first embodiment, and a detailed method of setting the image reading sensitivity (charge accumulating period) will be described below.

In S32 (image data conversion step) of FIG. 14, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via an amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to a data comparator 124. In this case, the lightness data is expressed by, e.g., 256 gray levels.

In S33 (step of extracting the maximum and minimum values of each row) of FIG. 14, the data comparator 124 extracts the maximum and minimum values of lightness data of each row, and outputs them to an adder 125. That is, the data comparator 124 extracts lightness data representing a maximum value (gray level value of the brightest pixel) contained in each row, and

lightness data representing a minimum value (gray level value of the darkest pixel).

5 In S34 (step of calculating the dynamic range of each row) of FIG. 14, the adder 125 calculates as a dynamic range the difference between the maximum and minimum values of lightness data of each row, and stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range calculation processing for all the rows.

10 In S35 (step of calculating the linearly differentiated value of the dynamic range) of FIG. 14, the dynamic ranges of respective rows stored in the RAM 130 are read out via the data selector 126, and input again to the adder 125, which calculates the difference (linearly differentiated value) between the dynamic ranges of adjacent rows. The results are stored in the RAM 130 via the data selector 126.

20 In S36 (step of extracting a row number having a maximum dynamic range and minimum linearly differentiated value) of FIG. 14, data of the dynamic ranges of respective rows and data of the linearly differentiated values of the dynamic ranges which are stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, 25 which extracts a row number at which the dynamic range maximizes and the linearly differentiated value of the dynamic range minimizes (to 0 or a value close to 0).

In S37 (sensitivity referring/extraction step) of FIG. 14, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is looked up based on the extracted row number, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

In S38 (extracted sensitivity setting step) of FIG. 14, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity. In S39 (subject image reading step) of FIG. 14, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the third embodiment of the photosensor system drive control method to a fingerprint reading apparatus will be described with reference to FIGS. 15 to 18B.

FIG. 15 is a view showing an example of image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIG. 16 is a graph showing changes in lightness data of respective pixels of several rows in the column direction that are based on the subject image data obtained by the sensitivity-adjusting

reading operation. FIGS. 17A and 17B are graphs showing the relationship between changes in the dynamic ranges of respective rows and changes in the linearly differentiated values of the dynamic ranges of
5 respective rows. FIGS. 18A and 18B are views for illustrating tables showing the relationship between the dynamic range of each row and the linearly differentiated values of the dynamic range that are obtained by the sensitivity-adjusting reading
10 operation, and a row number vs. image reading sensitivity correspondence table. Assume that image data are read out in units of a matrix pattern of 256 rows \times 196 columns. A larger lightness data value represents a brighter image, and a smaller lightness
15 data value represents a darker image.

In the sensitivity-adjusting reading operation, the image reading sensitivity is set higher (charge accumulating period is set longer) for a larger row number (upward in FIG. 15), and lower (charge
20 accumulating period is set shorter) for a smaller row number (downward in FIG. 15). In FIG. 15, as the row number increases (upward in FIG. 15), the ridge/valley pattern of the fingerprint becomes weaker under the influence of external light, and at last is read as an
25 almost invisibly bright image. On the other hand, as the row number decreases (downward in FIG. 15), the ridge/ valley pattern of the fingerprint becomes

darker, and at last is read as an almost invisibly dark image. The lightness data level is expressed by 256 gray levels, and its lower and upper limit values are set to 0 and 255, respectively.

5 In this image data, a sensitivity determination range used to extract a row having an optimal sensitivity is preferably limited to a region having a fine contrast corresponding to the ridge/valley pattern of the fingerprint. This embodiment will exemplify
10 sensitivity setting processing when a row/column range defined by 64th to 191st rows and 67th to 130th columns is set as the sensitivity determination range.

 In the sensitivity determination range shown in FIG. 15, for example, changes in lightness data in
15 the 64th, 96th, 160th, and 191st rows are extracted and plotted as shown in FIG. 16. In the 191st row (represented by the broken line in FIG. 16) and 160th row (represented by the thin line in FIG. 16) within the row range, the sensitivity is set high, and
20 lightness data converges to a large value (about 220 to 225) and hardly provides any information as image data. In the 96th row (represented by the thick line in FIG. 16), lightness data does not converge to either the upper or lower limit value on all the columns, and
25 exhibits a relatively large vertical displacement corresponding to the bright/dark pattern of image data. In the 64th row (represented by the chain line in

FIG. 16), the sensitivity is set low, so that lightness data converges to a small value (about 35) and hardly provides any information as image data.

Maximum and minimum values are extracted from
5 the lightness data distribution of each row, and the difference is calculated to obtain a dynamic range. Obtained dynamic ranges are plotted for row numbers to attain a distribution curve having a maximum value MA in a predetermined row, as shown in FIG. 17A.
10 Further, linear differentiation for the dynamic range distribution, i.e., the slopes of the dynamic range distribution curve for respective rows are calculated, and plotted for row numbers. As shown in FIG. 17B, a linearly differentiated value MB is 0 in a row
15 exhibiting the maximum value MA.

It can be determined that lightness data in the row exhibiting the maximum dynamic range and minimum linearly differentiated value is image data having a fine contrast corresponding to the ridge/valley
20 pattern of a fingerprint, and an optimal image reading sensitivity is set.

Maximum and minimum values are extracted as numerical data on the basis of changes in the lightness data distribution of each row shown in FIG. 16, and
25 a dynamic range calculated from the difference and a linearly differentiated value calculated from the difference of the dynamic range of each row are listed

on a table as shown in FIG. 18A.

In FIG. 18A, when the dynamic range maximizes at R_k in FIG. 18A, and the linearly differentiated value minimizes at D_{k-1} in FIG. 18A, rows L_{k-1} and L_k are
5 extracted as row numbers at which the dynamic range maximizes and the linearly differentiated value minimizes.

As shown in FIG. 6B, the RAM 130 stores a row
number vs. image reading sensitivity correspondence
10 table within the sensitivity determination range, and stores image reading sensitivities, i.e., charge accumulating periods T_{64} to T_{191} for respective row numbers.

This row number vs. image reading sensitivity
15 correspondence table is looked up for the extracted rows to extract image reading sensitivities, i.e., charge accumulating periods T_{k-1} and T_k set for the rows L_{k-1} and L_k , which are determined as optimal values. The sensitivity setting register 127 is
20 rewritten to set, as an optimal image reading sensitivity, a set value determined based on the two extracted charge accumulating periods T_{k-1} and T_k , i.e., the average of the charge accumulating periods T_{k-1} and T_k . A subject (fingerprint) image is read at
25 this optimal image reading sensitivity.

Note that in the distributions of the dynamic range and linearly differentiated value shown in

FIGS. 17A and 17B, the linearly differentiated value of a row whose dynamic range has the maximum value MA is 0. In practice, however, a row whose linearly differentiated value is 0 may not exist. Thus, as
5 conditions for extracting a row set to an optimal sensitivity, a row exhibiting the maximum dynamic range and the minimum linearly differentiated value (value nearest to 0) is extracted.

As will be described below, the third embodiment
10 can effectively prevent any malfunction in optimal sensitivity extraction processing even when lightness data contains an abnormal value due to a small foreign substance attached to the fingerprint reading surface of the photosensor, a defect of the photosensor, or
15 the like. This will be explained with reference to FIGS. 19A to 22B.

FIGS. 19A and 19B are tables showing the relationship between the dynamic range distribution of respective rows and a row number vs. image reading
20 sensitivity correspondence table when the first embodiment is applied as another setting method of setting the optimal sensitivity of the photosensor system. According to this setting method, the optimal value of the image reading sensitivity is determined
25 using a row whose dynamic range has the maximum value MA in the dynamic range distribution (see FIG. 17A) of lightness data in sensitivity setting processing

described above.

In this sensitivity setting method, as described above, the dynamic range is calculated based on the lightness data distribution (maximum and minimum values) of each row in FIG. 19A, a row (L_k in FIG. 19A) having the maximum value (e.g., R_k in FIG. 19A) is extracted, and an image reading sensitivity (charge accumulating period T_k) set for the row L_k is extracted and determined as an optimal value.

Operation processing when lightness data contains an abnormal value, and comparison with the third embodiment will be explained.

FIG. 20 is a view showing still another example of image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIG. 21 is a graph showing changes in the dynamic ranges of respective rows. FIGS. 22A and 22B are graphs showing the relationship between changes in the dynamic ranges of respective rows, and changes in the linearly differentiated values of the dynamic ranges of respective rows.

As shown in FIG. 20, the sensitivity determination range is set to a row/column range defined by 64th to 191st rows and 67th to 130th columns, similar to FIG. 15, as a region having a fine contrast corresponding to the ridge/valley pattern of a fingerprint in

order to extract a row having an optimal sensitivity from image data of the fingerprint. In this case, if an abnormal pixel IL1 exists in a row L within the sensitivity determination range owing to a foreign substance attached to a fingerprint reading surface, a defect of the photosensor, or the like, lightness data of the abnormal pixel IL1 may exhibit an excessive value in comparison with peripheral pixel data. This occurs when, for example, a black point exists on the white background, or a white point exists on the black background. In the distribution of a dynamic range calculated based on the maximum and minimum values of lightness data, the dynamic range of the row L containing the abnormal pixel IL1 appears greatly apart from the change trend of the entire distribution. If the setting method of the first embodiment in which an image reading sensitivity corresponding to a row having the maximum dynamic range is adopted as an optimal value is applied to image data read in the sensitivity-adjusting reading operation, the dynamic range of the row L containing the abnormal pixel IL1 that is irrelevant to an original maximum value MA1 in the change trend of the dynamic range distribution is extracted as a maximum value MA2, and an image reading sensitivity set for the row L having this dynamic range is determined to be an optimal value. In this case, an improper image reading sensitivity (e.g., charge

accumulating period longer than an optimal value) is set in the photosensor system. In normal reading operation, accurate reading operation may fail such that a subject image becomes white.

5 To the contrary, the sensitivity setting method of the third embodiment sets an optimal image reading sensitivity using conditions of extracting a row number at which the dynamic range exhibits the maximum value MA1 and the linearly differentiated value of the
10 dynamic range exhibits a minimum value MB1 within a range where the dynamic range coincides with the entire dynamic range change trend. For this reason, the third embodiment does not extract, as a row corresponding to an optimal reading sensitivity,
15 the row L containing the abnormal pixel IL1 in which a dynamic range value MA2 in FIG. 22A deviates from the dynamic range change trend and is a maximum value, but a linearly differentiated value MB2 of the dynamic range in FIG. 22B is not a minimum value.

20 Hence, even when a subject image contains the abnormal pixel IL1 due to a foreign substance attached to a fingerprint reading surface, a defect of the photosensor, or the like, a row having a fine contrast corresponding to the ridge/valley pattern of a finger-
25 print can be reliably extracted to determine an optimal charge accumulating period.

 According to the sensitivity setting method of the

third embodiment, sensitivity-adjusting reading operation is executed while the image reading sensitivity is changed stepwise for respective rows. A row in an optimal image reading state is easily and properly determined based on the dynamic range value of each row to lightness data and the linearly differentiated value of the dynamic range. An image reading sensitivity (charge accumulating period) set for the row can be set as an optimal sensitivity.

Normal image reading operation of a subject image can be performed at a proper sensitivity without being influenced by an abnormal pixel generated by a foreign substance attached to a fingerprint reading surface, a defect of the photosensor, or the like.

The third embodiment executes sensitivity setting processing in a sensitivity determination range limited to a row/column range defined by 64th to 191st rows and 67th to 130th columns. However, the present invention is not limited to this, and is applicable to the entire region of image data without limiting the sensitivity determination range.

<Fourth Embodiment>

The fourth embodiment of a photosensor system drive control method according to the present invention to which the same controller 120 as in the third embodiment can be applied will be described with reference to the several views of the accompanying

drawing. The fourth embodiment determines whether an abnormal pixel exists in image data by applying the sensitivity setting method of the third embodiment.

FIG. 23 is a flow chart showing an operation up to
5 detection processing of an abnormal pixel according to the fourth embodiment in the photosensor system operation control method using the above-mentioned controller 120.

In S41 (sensitivity-adjusting reading operation)
10 of FIG. 23, a main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in a sensitivity setting register 127 via a data controller 122, and executes the
15 sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise for respective rows of the subject image. These operations are executed prior to normal reading operation of a subject image, for example. The image
20 reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspondence table in a RAM 130 in correspondence with row numbers. This sensitivity-adjusting reading operation is the same as the operation in the first
25 embodiment, and a detailed method of setting the image reading sensitivity (charge accumulating period) will be described below.

In S42 (image data conversion step) of FIG. 23, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via an amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to a data comparator 124. In this case, the lightness data is expressed by, e.g., 256 gray levels.

In S43 (step of extracting the maximum and minimum values of each row) of FIG. 23, the data comparator 124 extracts the maximum and minimum values of lightness data of each row, and outputs them to an adder 125. That is, the data comparator 124 extracts lightness data representing a maximum value (gray level value of the brightest pixel) contained in each row, and lightness data representing a minimum value (gray level value of the darkest pixel).

In S44 (step of calculating the dynamic range of each row) of FIG. 23, the adder 125 calculates as a dynamic range the difference between the maximum and minimum values of lightness data of each row, and stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range calculation processing for all the rows.

In S45 (step of calculating the linearly differentiated value of the dynamic range) of FIG. 23, the dynamic ranges of respective rows stored in the RAM

130 are read out via the data selector 126, and input again to the adder 125, which calculates the difference (linearly differentiated value) between the dynamic ranges of adjacent rows. The results are stored in
5 the RAM 130 via the data selector 126.

In S46 (step of extracting a row number having a maximum dynamic range and maximum linearly differentiated value) of FIG. 23, data of the dynamic ranges of respective rows and data of the linearly
10 differentiated values of the dynamic ranges which are stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number at which the dynamic range maximizes and the linearly differentiated value of the
15 dynamic range maximizes.

In S47 (step of determining presence/absence of an extracted row) of FIG. 23, whether a corresponding row number has been extracted in step S46, i.e., whether a row which satisfies extraction conditions
20 exists is determined. If a corresponding row number is determined based on the determination result to have been extracted, an abnormal pixel is determined to exist in the image data read by the sensitivity-adjusting reading operation. If no corresponding row
25 number is determined to have been extracted, no abnormal pixel is determined to exist.

This abnormal pixel detection processing can

determine the presence/absence of a foreign substance attached to the read surface for a subject or the subject itself, or the presence/absence of a defect of the sensor element constituting the photosensor array.

5 If an abnormal pixel exists, this can be notified with an alarm or the like to execute proper action, and normal reading operation of a subject image can be appropriately done in S48.

10 More specifically, as shown in FIG. 20, a predetermined sensitivity determination range is set on image data of a fingerprint. At this time, if the abnormal pixel IL1 exists in the sensitivity determination range due to a foreign substance attached to a fingerprint reading surface, characteristic
15 changes and defects of the photosensor, or the like, lightness data of the abnormal pixel IL1 exhibits an excessive value in comparison with peripheral pixel data. In this case, a dynamic range calculated based on the maximum and minimum values of this lightness
20 data, and its linearly differentiated value appear greatly apart from the remaining normal distribution trend, as shown in FIGS. 21, 22A, and 22B. When the abnormal detection method of the fourth embodiment is applied to this situation, a row number L at which the
25 dynamic range exhibits the maximum value MA2 and the linearly differentiated value of the dynamic range exhibits the maximum value MB2 is extracted to

determine that the abnormal pixel IL1 exists in the image data. As a result, proper action of, e.g., cleaning the sensing surface to remove the foreign substance can be instructed prior to normal reading operation of a subject image.

Note that the abnormal detection method of the fourth embodiment may be executed singly for a predetermined subject image, or may be executed in parallel with the above-described sensitivity setting method.

<Fifth Embodiment>

The fifth embodiment of a photosensor system drive control method according to the present invention will be described with reference to the several views of the accompanying drawing.

The detailed arrangement and operation of a controller applied to the fifth embodiment will be explained with reference to the several views of the accompanying drawing.

FIG. 24 is a block diagram showing an arrangement of the controller 120a applied to this embodiment. As will be described below, this controller 120a has almost the same arrangement as the controller 120 shown in FIG. 2, and the same reference numerals denote the same parts.

As shown in FIG. 24, a controller 120a in the fifth embodiment comprises a device controller 121 for

controlling a top gate driver 111, bottom gate driver 112, and output circuit section 113, a data controller 122 for managing various data such as image data, write data, and readout data to a RAM 130, and a main controller 123 which supervises the controllers 121 and 122 and interfaces with an external function section.

The controller 120a further comprises:

an abnormal value removing section 128 constituted by a Fourier transformation section or circuit 128a for Fourier-transforming specific measurement data based on image data input as a digital signal from a photosensor array 100 via an A/D converter 117, a filtering section or circuit 128b for removing a high-frequency component corresponding to an abnormal value from the Fourier-transformed measurement data, and an inverse Fourier transformation section or circuit 128c for inversely Fourier-transforming the measurement data from which the high-frequency component is removed;

a data comparator 124 for extracting maximum and minimum values by comparing the sizes of measurement data from which abnormal values are removed by the abnormal value removing section 128, and for extracting the maximum value of a dynamic range calculated by an adder 125 (to be described below) and the minimum value of the difference (linearly differentiated value) between dynamic ranges;

the adder 125 for calculating a dynamic range from

the difference between the maximum and minimum values of measurement data, and calculating the difference between dynamic ranges, i.e., linearly differentiated value;

5 a data selector 126 for receiving measurement data processed via the A/D converter 117, abnormal value removing section 128, data comparator 124, and adder 125, and switching write/readout in/from the RAM 130, re-input to the data comparator 124 and adder 125, and
10 output to the external function section 200 via the data controller 122 in accordance with the received data; and

 a sensitivity setting register 127 for changing control signals to be output from the device controller
15 121 to the top and bottom gate drivers 111 and 112 so as to optimize the reading sensitivity of the photosensor array on the basis of a control signal from the data controller 122.

 The operation of the fifth embodiment in the
20 operation control method of the photosensor system using the above controller 120a will be explained with reference to FIG. 25. FIG. 25 is a flow chart showing an operation up to read of a subject image with an optimal sensitivity according to the fifth embodiment
25 in operation control of the photosensor system.

This operation will be described by properly referring to the arrangement of the photosensor system shown in

FIGS. 1 and 24.

In S51 (sensitivity-adjusting reading operation) of FIG. 25, the main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting
5 reading operation in the sensitivity setting register 127 via the data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise
10 for respective rows of the subject image. The image reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspondence table in the RAM 130 in correspondence with row numbers. This sensitivity-adjusting reading
15 operation is the same as the operation in the first embodiment, and a detailed method of setting the image reading sensitivity (charge accumulating period) will be described below.

In S52 (image data conversion step) of FIG. 25,
20 the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via the amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to the abnormal value
25 removing section 128. In this case, the lightness data is expressed by, e.g., 256 gray levels.

In S53 (Fourier transformation step) of FIG. 25,

the lightness data input to the abnormal value removing section 128 is Fourier-transformed by the Fourier transformation section 128a on the basis of the dynamic range of lightness data of each row to obtain
5 a frequency distribution representing the variation width of lightness data of each row number.

In S54 (high-frequency component removing step) of FIG. 25, a high-frequency component equal to or higher than a predetermined value is removed from
10 the lightness data frequency distribution converted by the Fourier transformation section 128a. More specifically, a predetermined high-frequency component is removed by passing the data through the filtering section 128b formed from, e.g., a low-pass filter.

15 In S55 (inverse Fourier transformation step) of FIG. 25, the frequency distribution from which the high-frequency component is removed is inversely Fourier-transformed by the inverse Fourier transformation section 128c to obtain lightness data of each row
20 number again.

A series of abnormal value removing operations of the abnormal value removing section 128 remove from original lightness data a high-frequency component, i.e., abnormal value which has a steep variation and
25 deviates from the main change trend of lightness data, and extract only the main component of the lightness data in which the dynamic range changes smoothly for

each row. The lightness data from which the abnormal value is removed is input to the data comparator 124.

5 In S56 (step of extracting the maximum and minimum values of each row) of FIG. 25, the data comparator 124 extracts for each row the maximum and minimum values of the lightness data from which the abnormal value is removed, and outputs them to the adder 125. That is, the data comparator 124 extracts lightness data representing a maximum value (gray level value of the
10 brightest pixel) contained in each row, and lightness data representing a minimum value (gray level value of the darkest pixel).

In S57 (step of calculating the dynamic range of each row) of FIG. 25, the adder 125 calculates as
15 a dynamic range the difference between the maximum and minimum values of lightness data of each row, and temporarily stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range calculation processing for all the rows.

20 In S58 (step of calculating the linearly differentiated value of the dynamic range) of FIG. 25, the dynamic ranges of respective rows stored in the RAM 130 are read out via the data selector 126, and input again to the adder 125, which calculates the difference
25 (linearly differentiated value) between the dynamic ranges of adjacent rows. The results are stored in the RAM 130 via the data selector 126.

In S59 (step of extracting a row number having a maximum dynamic range and minimum linearly differentiated value) of FIG. 25, data of the dynamic ranges of respective rows and data of the linearly differentiated values of the dynamic ranges which are stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number at which the dynamic range maximizes and the linearly differentiated value of the dynamic range minimizes (to 0 or a value close to 0).

In S60 (sensitivity referring/extraction step) of FIG. 25, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is looked up based on the extracted row number, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

In S61 (extracted sensitivity setting step) of FIG. 25, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity. In S62 (subject image reading step) of FIG. 25, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the fifth embodiment of the photosensor system drive control method to a

fingerprint reading apparatus will be described with reference to FIGS. 26 to 27B.

As will be described below, the fifth embodiment can effectively prevent any malfunction in optimal sensitivity extraction processing even when image data read by the sensitivity-adjusting reading operation contains an abnormal value, and the abnormal value exists on not only one pixel but across a plurality of pixels. This embodiment can also be effectively applied to a case wherein image data does not contain any abnormal value, which will be described first.

The sensitivity-adjusting reading operation in the fifth embodiment is the same as that in the above embodiments. The fifth embodiment will exemplify a case wherein image data read by the sensitivity-adjusting reading operation is the same as image data shown in FIG. 15, and the sensitivity determination range is defined to a row/column range of 64th to 191st rows and 67th to 130th columns.

The result of extracting changes in lightness data in the 64th, 96th, 160th, and 191st rows in the sensitivity determination range and plotting them is the same as FIG. 16.

In accordance with the above-mentioned abnormal value removing operation, the lightness data distribution of respective rows is Fourier-transformed to obtain a frequency distribution for the row number,

a high-frequency component corresponding to an abnormal value or noise is removed, and the resultant data is inversely Fourier-transformed to extract only lightness data representing a main change trend in the lightness data distribution of respective rows. In this case, image data does not contain any abnormal value.

Thus, even if the high-frequency component of lightness data is removed, the lightness data distribution trend does not especially change. Hence, the dynamic range distribution of respective rows is the same as that shown in FIG. 17A. Changes in the linearly differentiated values of respective rows to this dynamic range distribution are also the same as those shown in FIG. 17B. For this reason, a row number extracted under conditions that the dynamic range is maximum and the linearly differentiated value is minimum is the same as in the third embodiment, and an optimal image reading sensitivity based on the extracted row number is also the same as in the third embodiment.

The following description concerns sensitivity setting operation when image data contains an abnormal value owing to a foreign substance attached to a subject or the sensing surface of the photosensor array, a defect of the sensor element constituting the photosensor array, or the like.

FIG. 26 is a view showing an example of image data when a subject (fingerprint) image is read while the

image reading sensitivity is changed stepwise for
respective rows in sensitivity-adjusting reading
operation. FIG. 27A is a graph showing the dynamic
range distribution of lightness data of respective rows
when a subject image has a component corresponding to a
foreign substance or the like. FIG. 27B is a graph
showing the dynamic range distribution of lightness
data of respective rows after abnormal value removing
operation according to the fifth embodiment.

As shown in FIG. 26, similar to the above-
described case, a row/column range of 64th to 191st
rows and 67th to 130th columns is set as a sensitivity
determination range for read fingerprint image data.
In this case, if an abnormal pixel IL2 relatively large
enough to overlap a plurality of rows (LA to LB rows)
exists in the sensitivity determination range owing to
a foreign substance attached to the sensing surface of
the photosensor array, a defect of the photosensor
element, noise contained in image data, or the like,
the lightness data of the abnormal pixel IL2 may
exhibit an excessive value in a plurality of rows in
comparison with peripheral pixel data, i.e., a value
deviating from the change trend of peripheral pixel
data. This occurs when, e.g., a relatively large black
point exists on the white background, or a relatively
large white point exists on the black background, and
more specifically, when the variation width or dynamic

range of lightness data discretely varies in respective rows, or abnormal pixel data MC due to a foreign substance attached to the sensing surface or a defect of an element exists across a plurality of rows (LA to LB rows), as shown in FIG. 27A.

If the sensitivity setting method of the third embodiment is applied without performing abnormal value removing operation, this sensitivity setting method extracts a row in which the dynamic range of lightness data for each row is maximal and the linearly differentiated value is minimal as a row having an optimal image reading sensitivity. Thus, the dynamic ranges of rows on which the abnormal pixel IL2 continuously exists may be recognized to exhibit a maximum value with respect to the main distribution trend of the whole dynamic range. In addition, the linearly differentiated value in a region representing a continuous change exhibits a value close to 0, and may be recognized to be a minimum value. As a result, a row (row between LA and LB) containing the abnormal pixel IL2 irrelevant to a row having an original optimal image reading sensitivity may be mistaken as a row corresponding to an optimal image reading sensitivity. In this case, an improper image reading sensitivity (e.g., charge accumulating period longer than an optimal value) is set in the photosensor system. In normal reading operation, a subject image

may become, e.g., white.

To the contrary, the sensitivity setting method of the fifth embodiment can remove any abnormal value contained in lightness data by performing Fourier transformation to remove a high-frequency component corresponding to an abnormal value or noise prior to processing of obtaining the optimal value of the reading sensitivity based on the dynamic range of lightness data. As shown in FIG. 27B, an abnormal value greatly deviating from the dynamic range distribution trend of lightness data for the row number is eliminated, and only smoothed lightness data MD representing a main change trend is extracted. On the basis of the extracted lightness data MD, a row corresponding to a maximum value MA3 of the dynamic range shown in FIG. 27B is extracted as a row having an optimal image reading sensitivity under the conditions that the dynamic range is maximum and the linearly differentiated value of the dynamic range is minimum.

Even when a subject image contains the abnormal pixel IL2 relatively large enough to overlap a plurality of rows owing to a foreign substance attached to the sensing surface of the photosensor array, a defect of the photosensor element, noise contained in image data, or the like, a row having a fine contrast corresponding to the ridge/valley pattern of a fingerprint can be reliably extracted to determine

an optimal charge accumulating period. The fifth embodiment can therefore provide a fingerprint reading apparatus capable of reading a high-quality fingerprint image with almost no malfunction.

5 Note that the fifth embodiment executes sensitivity setting processing while the sensitivity determination range is limited to a row/column range of 64th to 191st rows and 67th to 130th columns. However, the embodiment is not limited to this, and can also be
10 applied to a case wherein sensitivity setting processing is executed for the entire region of image data without limiting the sensitivity determination range.

<Sixth Embodiment>

15 The sixth embodiment of a photosensor system drive control method according to the present invention will be described with reference to the accompanying drawings.

 In the first to fifth embodiments described above,
20 the sensitivity-adjusting reading operation is performed, with the image reading sensitivity being changed stepwise for each of the rows of the photosensor array, and one subject image is thereby read at a plurality of different densities. In the
25 sixth embodiment, the image reading sensitivity of the photosensors of one or several rows (hereinafter referred to as a specific row section) of the

photosensor array is changed stepwise, and the subject image portion corresponding to the specific row section is read. The controller applied to the sixth embodiment is similar in structure to the controller 120 employed in the first and second embodiments and represented by the structural blocks shown in FIG. 2.

FIG. 28 is a flowchart illustrating how the controller 120 controls the operation of the photosensor system in the sixth embodiment of the present invention. In the flowchart, the operations executed up to the optimal image reading sensitivity setting are illustrated. FIG. 29 shows a specific row section of the photosensor array for which the sensitivity-adjusting reading operation is performed according to the sixth embodiment, the specific row section being illustrated as $n/2$ in relation to a subject image. In the description below, reference will be made to the structure of the photosensor system shown in FIGS. 1 and 2, if required.

In S71 (sensitivity-adjusting reading operation) of FIG. 28, the main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in the sensitivity setting register 127 via the data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise

for respective specific row section of the subject image. These operations are executed prior to the normal reading operation of the subject image, for example. It should be noted that the sensitivity-adjusting reading operation applicable to the sensitivity adjusting method of the sixth embodiment is performed, using a photosensor array 100 in which photosensors are arranged in units of a matrix pattern of 256 rows \times 196 columns, as shown in FIG. 29. In this photosensor array, a central row (i.e., the $n/2$ -th row) or several rows in the vicinity thereof are regarded as a specific row section, and the photosensors 10 corresponding to the specific row section are reset. Thereafter, precharge operation and readout operation are repeatedly executed at predetermined timings in such a manner that the charge accumulating period (image reading sensitivity) varies stepwise. In other words, the image reading sensitivity is made to vary in correspondence to the number of times reading operation is executed. Data are stored in a RAM 130, for example, in a table format of (the number of times of reading operation) vs (image reading sensitivity correspondence table). A specific method for setting the image reading sensitivity will be described later.

In S72 (image data conversion step) of FIG. 28, the image data read by the sensitivity-adjusting

reading operation are converted into digital signals via an amplifier 116 and an A/D converter 117. The digital signal is supplied to a data comparator 124 of the controller 120 as lightness data corresponding to the bright/dark pattern of the subject image. The lightness data are expressed by, e.g., 256 gray levels. The image data corresponding to each reading operation are converted into a lightness data value in the range of 0 to 255 and stored in the data comparator 124. A specific example is shown in FIGS. 30A to 30E. FIGS. 30A to 30E show lightness data which are obtained when reading operation has been executed a predetermined number of times, and in which the image reading sensitivity increases with an increase in the number of times reading operation is executed. For example, FIGS. 30A to 30E show how lightness data change in the columns when reading operation has been executed 16 times (FIG. 30A), 32 times (FIG. 30B), 64 times (FIG. 30C), 96 times (FIG. 30D) and 128 times (FIG. 30E). The lightness data obtained when the reading operation has been executed 16 times and 32 times are data wherein the image reading sensitivity is low. Since the sensitivity is thus insufficient, there are columns in which the data value is "0" (lower limit). On the other hand, the lightness data obtained when the reading operation has been executed 96 times and 128 times are data wherein the image reading sensitivity is

high. Since the sensitivity is too high, there are columns in which the data value is "255" (upper limit).

5 In S73 (the step of extracting a maximum value and a minimum value in each reading operation) of FIG. 28, a maximum value and a minimum value are extracted from the lightness data supplied to the data comparator 124. The extracted maximum and minimum values are output to the adder 125. In other words, the lightness data value indicating a maximum value (i.e., the gray level of the brightest pixel) and the lightness data value indicating a minimum value (i.e., the gray level of the darkest pixel) are extracted each time reading operation is executed.

10 Next, in S74 (the step of calculating a dynamic range in each reading operation) of FIG. 28, the adder 125 calculates the difference between the maximum and minimum values of lightness data in each reading operation as a dynamic range. The result of this calculation is stored in the RAM 130 through the use of the data selector 126. This dynamic range calculation step is executed each time reading operation is performed.

20 In S75 (the step of extracting a reading operation that exhibits a maximum dynamic range) of FIG. 28, the data selector 126 reads out dynamic ranges of reading operations from the RAM 130, and the readout dynamic ranges are supplied to the data comparator 124. On the

basis of the dynamic range changing tendency (FIG. 31) relative to the number of times of a reading operation is executed, a maximum value DLmax of the dynamic range is determined in relation to the number of times a reading operation is executed, and the number RCa of times corresponding to the determined maximum value is extracted. In the example shown in FIGS. 30A to 30E, the lightness data obtained in the 16th and 32nd reading operations have a minimum value saturated at the lower limit (=0), and the lightness data obtained in the 96th and 128th reading operations has a maximum value saturated at the upper limit (=255). In contrast, the lightness data obtained in the 64th reading operation does not have a value that is saturated at the upper or lower limit. As a result, the dynamic range of the lightness data obtained in the 64th reading operation is greater than the dynamic ranges of the other lightness data. Hence, the maximum value is DLmax, and the number RCa of the reading operation corresponding to that maximum value is 64.

Next, S76 (the step of referring to and extracting a sensitivity) of FIG. 28 is executed on the basis of the extracted number RCa. In the step, the image reading sensitivity (i.e., the charge accumulating period) corresponding to the number RCa of the reading operation is extracted by referring to the table stored in the RAM 130, i.e., the table of [the number of times

of reading operation] vs [image reading sensitivity correspondence table].

5 In S77 (the step of setting the extracted sensitivity) of FIG. 28, the main controller 123 causes the data controller 122 to rewrite the data in the sensitivity setting register 127, so that the image reading sensitivity of the sensitivity setting register 127 is set at the extracted image reading sensitivity. This brings an end to the optimal image reading sensitivity setting based on the sensitivity-adjusting reading operation.

10 According to the sensitivity setting method of the sixth embodiment, one or more specific rows (specific row section) of the photosensor array are selected, and the sensitivity-adjusting reading operation (which repeatedly reads a subject image at predetermined intervals) is executed in the selected specific row section after resetting operation. Hence, the subject image can be read, with the image reading sensitivity (charge accumulating period) being varied stepwise. In comparison with the case where resetting operation is repeated executed for each of the rows of the photosensor array, as in the first to fifth embodiments, the time needed for the sensitivity-adjusting reading operation can be as short as possible.

In the first to fifth embodiments, the

sensitivity-adjusting reading operation is executed for the entire light-receiving area or a selected light-receiving area of the photosensor array, and an optimal image reading sensitivity is extracted on the basis of the read image data corresponding to one frame. Unlike these embodiments, the sixth embodiment uses image data corresponding to one or several specific rows (specific row section). In comparison with the foregoing embodiments, the amount of data used for the extraction of an optimal image reading sensitivity can be significantly reduced, resulting in a remarkable decrease in the processing load. In addition, the time needed for the setting of an optimal image reading sensitivity can be significantly shortened.

Furthermore, the sensitivity-adjusting reading operation is limited to the specific row section. Unlike the first to fifth embodiments, wherein the sensitivity-adjusting reading operation is executed for the entire light-receiving area of the photosensor array or a selected portion thereof, the sixth embodiment has significantly lowered the probability of inclusion of an abnormal pixel (a missing point or a twinkling point), which may be caused by a foreign substance adhering to a target area, a defective element of a photosensor, or the like. Hence, there is a significantly lowered probability that an inappropriate image reading sensitivity will be set due

to the existence of such an abnormal pixel.

Accordingly, a malfunction is prevented in fingerprint recognition processing.

5 In the sixth embodiment, specific row section is a central row ($n/2$ -th row) and several rows located in the vicinity thereof in a matrix of n rows \times m columns ($n = 256$, $m = 196$). Needless to say, the present invention is not limited to this. The specific row section may be selected from any area as long as that
10 area shows a clear brightness pattern (contrast) of a subject image. For example, the specific row section may be those located near the central row, or may be selected from another area.

<Seventh Embodiment>

15 The seventh embodiment of a photosensor system drive control method according to the present invention will be described with reference to the accompanying drawings.

20 In the sixth embodiment described above, the sensitivity-adjusting reading operation is executed for one or several specific rows (specific row section). This significantly reduces the probability that an abnormal pixel exists in the target specific row section in comparison with the case where the entire light-receiving area of a photosensor array or a selected
25 area thereof is subjected to the reading operation. However, the probability that an abnormal pixel exists

in the specific row section is in no way "zero."

Like the sixth embodiment, the seventh embodiment is intended to reliably prevent the adverse effects an abnormal pixel may have when the sensitivity-adjusting reading operation is performed for the specific row section. The controller applied to the seventh embodiment is similar in structure to the controller 120 employed in the first, second and sixth embodiments and is represented by the structural blocks shown in FIG. 2.

FIG. 32 is a flowchart illustrating how the controller 120 controls the operation of the photosensor system in the seventh embodiment of the present invention. In the flowchart, the operations executed up to the optimal image reading sensitivity setting are illustrated. FIG. 33 shows a specific row section of the photosensor array for which the sensitivity-adjusting reading operation is performed according to the seventh embodiment, the specific row section being illustrated as R_p in relation to a subject image. In the description below, reference will be made to the structure of the photosensor system shown in FIGS. 1 and 2, if required. Similar or corresponding structural elements will be denoted by the same reference numerals as used in the description of the sixth embodiment, and a simplified description will be given of such structural elements.

The sensitivity-adjusting reading operation applied to the sensitivity adjusting method of the seventh embodiment is executed for a specific row R_p of a photosensor array 100 in which photosensors are arranged in units of a matrix pattern of 256 rows \times 196 columns, as shown in FIG. 33. In the description below, it is assumed that an abnormal pixel IL3 exists at the position of row R_p and column L_q , and that the value of the lightness data at that position is "0", due to a foreign substance adhering to the sensing surface of the photosensor array, a defective element of the photosensor, or the like.

Step S81 (sensitivity-adjusting reading operation) of FIG. 32 is executed in a similar manner to that of S71 of the sixth embodiment. That is, the photosensors corresponding to the specific row R_p of the photosensor array 100 shown in FIG. 33 are controlled in such a manner that the charge accumulating period (i.e., the image reading sensitivity) varies stepwise at predetermined intervals. The sensitivity-adjusting reading operation is performed for a subject image at a plurality of image reading sensitivities, which correspond to the number of times reading operation has been executed. These operations are executed prior to the normal reading of the subject image.

Step S82 (image data conversion step) of FIG. 32, is executed in a similar manner to that of S72 of the

sixth embodiment. The image data read by the sensitivity-adjusting reading operation are converted into lightness data. The lightness data are supplied to the controller 120 and stored in the RAM 130. A specific example is shown in FIGS. 34A to 34E. Like FIGS. 30A to 30E, FIGS. 34A to 34E show how lightness data change in the columns when reading operation has been executed 16 times (FIG. 34A), 32 times (FIG. 34B), 64 times (FIG. 34C), 96 times (FIG. 34D) and 128 times (FIG. 34E). The lightness data obtained when the reading operation has been executed 16 times and 32 times are data wherein the image reading sensitivity is low. Since the sensitivity is thus insufficient, there are columns in which the data value is "0" (lower limit). On the other hand, the lightness data obtained when the reading operation has been executed 96 times and 128 times are data wherein the image reading sensitivity is high. Since the sensitivity is too high, there are columns in which the data value is "255" (upper limit).

Next, step S83 (the step of extracting and comparing the same-column data from the data of each reading operation) shown in FIG. 32 is executed. In this step, the data selector 126 extracts lightness data of the same column from the lightness data stored in the RAM 130 and corresponding to each reading operation. The extracted lightness data are supplied

to the data comparator 124 so as to compare the lightness data of the same column.

Then, step S84 (the step of determining a variation in the same-column data) shown in FIG. 32 is executed. This step is for determining whether there is a column in which the lightness data remain the same after each reading operation.

If there is a column in which the lightness data do not changed, the pixels corresponding to this column are regarded as abnormal ones, and the specific row section for which the sensitivity-adjusting reading operation is performed is determined as containing an abnormal pixel.

If there is not a column in which the lightness data remain the same, the specific row section for which the sensitivity-adjusting reading operation is performed is determined as not containing an abnormal pixel.

A result of this determination is supplied from the data comparator 124 to the main controller 123. In the example shown in FIG. 37, the abnormal pixel IL3 is present, and the lightness data corresponding to column number Lq are "0" irrespective of the number of times reading operation is executed. In other words, there is a column in which the lightness data remain the same after each reading operation, and row Rq is determined to contain an abnormal pixel.

A description will be given of a specific method for checking the presence/absence of an abnormal pixel by detecting whether or not there is a column in which the lightness data do not changed before and after each reading operation. For example, the sensitivity-adjusting reading operation may be controlled as follows: Flags are set for the respective columns on the basis of the lightness data on the columns obtained by the first-time reading operation. The light data obtained by subsequent reading operations are compared with the lightness data obtained by the first-time reading operation. This comparison is executed for each of the columns. If the lightness data on a column differ from the original lightness data, the flag corresponding to that column is reset. As long as a pixel is normal, the lightness data on the pixel vary in accordance with a change in the image reading sensitivity. Hence, the flag of the pixel is reset. On the other hand, if the pixel is abnormal, the lightness data on the column containing the abnormal pixel do not vary even when the image reading sensitivity changes. The value of the lightness data is an upper-limit value, a lower-limit value or a constant in between, for example. Hence, the flag continues to be in the set state. As can be seen from this, an abnormal pixel present in a specific row section for which the sensitivity-adjusting reading

operation is to be executed can be detected by monitoring the states of the flags.

5 If step S84 (the step of determining a variation in the same-column data) determines that an abnormal pixel exists, step S85 (the step of changing the row section for which the sensitivity-adjusting reading operation) shown in FIG. 32 is executed. In this step, the main controller 123 causes the device controller 121 to change the specific row section for which the sensitivity-adjusting reading operation is to be executed. Thereafter, the operations starting from S81 (sensitivity-adjusting reading operation) are executed again. It is only required that the specific row section for which the sensitivity-adjusting reading operation is newly executed be a another specific row section other than the specific row section where the abnormal pixel IL3 is detected. For example, the another specific row section may be the one that is adjacent to row Rp in the upper or lower area, or may be the one that is away from that specific row section by a predetermined number of rows. The processing in steps S81-S84 is repeatedly executed until the specific row section for which the sensitivity-adjusting reading operation is to be executed is determined as not containing an abnormal pixel.

If step S84 (the step of determining a variation in the same-column data) determines that an abnormal

pixel does not exist in the specific row section for which the sensitivity-adjusting reading operation is to be executed, step S86 (the step of extracting a maximum value and a minimum value in each reading operation) shown in FIG. 32 is executed. In this step, maximum and minimum values are extracted from the lightness data obtained in each reading operation and supplied to the data comparator 124, and output to the adder 125, as in step S73 of the sixth embodiment.

Subsequently, step S87 (the step of calculating a dynamic range in each reading operation), step S88 (the step of extracting a reading operation that exhibits a maximum dynamic range), step S89 (the step of referring to and extracting a sensitivity) and step S90 (the step of setting the extracted sensitivity) shown in FIG. 32, are sequentially executed. These steps are similar to steps S74 to S77 of the sixth embodiment described above. That is, the dynamic range of the lightness data obtained in each reading operation is calculated by the adder, and then the data comparator 124 checks the dynamic range changing tendency (FIG. 31) relative to the number of times a reading operation is executed, and detects the reading operation in which the dynamic range is maximal. The image reading sensitivity (the charge accumulating period) corresponding to this reading operation is set in the sensitivity setting register 127, thereby bringing an end to the optimal

image reading sensitivity setting based on the sensitivity-adjusting reading operation.

5 In the sensitivity setting method of the seventh embodiment, if an abnormal pixel, which is due to a foreign substance adhering to the sensing surface of the photosensor array, any defective element of the photosensor, or the like, is present in the specific row section for which the sensitivity-adjusting reading operation is to be executed, such an abnormal pixel can be easily detected. Based on this detection, the sensitivity-adjusting reading operation is executed for another specific row section where no abnormal pixel exists. In this manner, lightness data corresponding to a specific row section containing no abnormal pixel is acquired as lightness data for sensitivity adjustment. Even if the specific row section originally selected for the sensitivity-adjusting reading operation contains an abnormal pixel, the adverse effects arising from such an abnormal pixel can be obviated.

10

15

20

In addition, an optimal image reading sensitivity is unconditionally determined on the basis of the dynamic range of light data acquired by the sensitivity-adjusting reading operation. Therefore, even when the sensitivity-adjusting reading operation is to be executed for a specific row section different from the originally selected specific row section, the

25

image reading sensitivity is kept optimal. Normal reading operation for a subject image can be executed in a reliable manner irrespective of the ambient conditions, such as the illuminated state of the environment. Accordingly, a malfunction is prevented in fingerprint recognition processing or the like.

In the sixth and seventh embodiments described above, the specific row section for which the sensitivity-adjusting reading operation is to be executed is predetermined, for example, in the center of the photosensor. The present invention is not limited to this. That is, the specific row section need not be designated beforehand. For example, the entire area of a subject image or a predetermined area thereof may be read at an arbitrary image reading sensitivity. In this case, a specific row section most suitable for image reading is extracted, and one or several rows of the specific row section may be determined on the basis of the extracted data. An image reading sensitivity (charge accumulating period) setting method applicable to the sensitivity-adjusting reading operation in the above-described embodiments will be described with reference to the several views of the accompanying drawing. In the description below, reference will be made to the structure of the photosensor system shown in FIGS. 1 and 2 and the structure of the photosensor system shown in FIGS. 39A

and 40, if required.

FIGS. 35A to 35J are timing charts showing the first embodiment of the image reading sensitivity (charge accumulating period) setting method, which is applicable to the sensitivity-adjusting reading operation of the first to fifth embodiments.

According to the image reading sensitivity setting method of this embodiment, as shown in FIGS. 35A to 35D, reset pulses ϕT_1 , ϕT_2 , ..., ϕT_n are simultaneously applied to respective top gate lines 101 connected to the top gate terminals TG of double-gate photosensors 10 in the row direction, thereby simultaneously starting a reset period T_{reset} , and initializing the double-gate photosensors 10 of respective rows.

The reset pulses ϕT_1 , ϕT_2 , ..., ϕT_n simultaneously fall to end the reset period T_{reset} . Then, charge accumulating periods T_1 , T_2 , ..., T_{n-1} , T_n of the double-gate photosensors 10 on all the rows simultaneously start, and charges (holes) are generated and accumulated in the channel regions in accordance with light quantities entering the double-gate photosensors 10 of respective rows from their top gate terminal (21) side.

As shown in FIGS. 35E to 35I, a pre-charge pulse ϕpg and readout pulses ϕB_1 , ϕB_2 , ..., ϕB_n corresponding to the bottom gate line 102 are applied

to change stepwise the charge accumulating periods T_1 , T_2 , ..., T_{n-1} , T_n set for respective rows by a predetermined delay time T_{delay} for respective rows. In this case, the delay time T_{delay} is equal to or longer than the total time of the reset period T_{reset} , pre-charge time T_{prch} , and readout time T_{read} .

As shown in FIG. 35J, therefore, drain voltages VD_1 , VD_2 , ..., VD_m varying in correspondence to the charge accumulated in the charge accumulating periods T_1 , T_2 , ..., T_n , which are between the end of the reset period T_{reset} and the start of the readout time T_{read} (i.e., the application of the readout pulses ϕB_1 , ϕB_2 , ..., ϕB_n), are sequentially read out.

Hence, image data read at reading sensitivities different for respective rows constituting a subject image can be attained by one reading operation of the subject image in sensitivity-adjusting reading operation performed prior to sensitivity setting processing as described in the above embodiments.

FIGS. 36A to 36J are timing charts showing the second embodiment of the image reading sensitivity (charge accumulating period) setting method, which is applicable to the sensitivity-adjusting reading operation of the first to fifth embodiments.

According to the image reading sensitivity setting method of this embodiment, as shown in FIGS. 36A to 36D, the reset pulses ϕT_1 , ϕT_2 , ..., ϕT_n are

sequentially applied to the respective top gate lines 101 connected to the top gate terminals TG of the double-gate photosensors 10 in the row direction at a time interval of a predetermined delay time T_{delay} , thereby starting the reset period T_{reset} , and initializing the double-gate photosensors 10 of respective rows.

The reset pulses $\phi T_1, \phi T_2, \dots, \phi T_n$ fall to end the reset period T_{reset} . Then, charge accumulating periods $TA_1, TA_2, \dots, TA_{n-1}, TA_n$ sequentially start, and charges (holes) are generated and accumulated in the channel regions in accordance with light quantities entering the double-gate photosensors 10 of respective rows from their top gate terminal (21) side.

As shown in FIGS. 36E to 36I, the pre-charge pulse ϕ_{pg} and readout pulses $\phi B_n, \phi B_{n-1}, \dots, \phi B_2, \phi B_1$ corresponding to the bottom gate line 102 are applied to change stepwise the charge accumulating periods $TA_1, TA_2, \dots, TA_{n-1}, TA_n$ set for respective rows by the predetermined delay time T_{delay} for respective rows after the final reset pulse ϕT_n falls. In this case, the delay time T_{delay} is equal to or longer than the total time of the reset period T_{reset} , pre-charge time T_{prch} , and readout time T_{read} .

As shown in FIG. 36J, therefore, drain voltages VD_1, VD_2, \dots, VD_m varying in correspondence to the charge accumulated in the charge accumulating periods

$TA_n, TA_{n-1}, \dots, TA_1$, which are between the end of the reset period T_{reset} and the start of the readout time T_{read} (i.e., the application of the readout pulses $\phi_{Bn}, \phi_{Bn-1}, \dots, \phi_{B1}$), are sequentially read out.

5 By this sensitivity-adjusting reading operation, the charge accumulating periods $TA_1, TA_2, \dots, TA_{n-1}, TA_n$ set for respective rows increase at a time interval twice the predetermined delay time T_{delay} , and thus image data read at reading sensitivities set at a
10 sensitivity adjustment width of several rows or more can be obtained by reading operation of one frame.

FIGS. 37A to 37L are timing charts illustrating an embodiment of the sensitivity-adjusting reading operation, which is applicable to the sensitivity-adjusting reading operation of the sixth and seventh
15 embodiments. In the description below, it is assumed that the one specific row section for which the sensitivity-adjusting reading operation is to be executed is a row located in the center.

20 As shown in FIGS. 37A to 37E, the image reading sensitivity setting method of the embodiment initializes only the double-gate photosensors of a central row ($n/2$ -th row), i.e., a specific row, of the photosensor array shown in FIG. 40. More specifically,
25 waves ϕ_{T1} to $\phi_{Tn/2-1}$ and $\phi_{Tn/2+1}$ to ϕ_{Tn} applied to the first to $(n/2-1)$ -th rows and $(n/2+1)$ -th to n -th rows, which are among the top gate lines 101 connected

to the top gate terminals TG of the double-gate
photosensors 10 in the row direction, are set at a low
level, and a single reset pulse $\phi_{Tn/2}$ is applied only
to the $n/2$ -th row. In this manner, the reset period
5 T_{reset} is started, and only the double-gate
photosensors 10 of the $(n/2)$ -th row are initialized.

Then, the reset pulse $\phi_{Tn/2}$ falls and the reset
period T_{reset} ends. Thereafter, the charge
accumulating period starts, and charges (holes) are
10 generated and accumulated in the channel regions in
accordance with the amount of light entering the
double-gate photosensors 10 of the $n/2$ -th row from
their top gate terminal (21) side.

Subsequently, as shown in FIGS. 37F to 37K,
15 precharge signal ϕ_{pg} and readout pulse $\phi_{Bn/2}$, which is
predetermined for the bottom gate lines 102 of the $n/2$ -
th row, are alternately applied at predetermined
intervals T_{int} a number of times (x times, x : an
integer larger than 1). Waves ϕ_{B1} to $\phi_{Bn/2-1}$ and
20 $\phi_{Bn/2+1}$ to ϕ_{Bn} applied to the bottom gate lines 102 of
the first to $(n/2-1)$ -th rows and $(n/2+1)$ -th to n -th
rows are set at a low level.

As shown in FIG. 37L, therefore, drain voltages
 VD_1, VD_2, \dots, VD_m varying in correspondence to the
25 charge accumulated in the charge accumulating periods
 TB_1, TB_2, \dots, TB_x , which are between the end of the
reset period T_{reset} and the start of the readout time

T_{read} (i.e., the application of the readout pulses $\phi_{Bn/2}$), are sequentially read out.

By this sensitivity-adjusting reading operation, the charge accumulating period of a specific row section increases stepwise at predetermined time intervals T_{int} . Hence, image data is read from a subject image, with the image corresponding to the specific row section being read at a plurality of different image reading sensitivities.

In the sensitivity-adjusting reading operation described above, the photosensors corresponding to one of the specific row section are reset at a time, and reading operation is repeatedly executed with respect to them. In this connection, it should be noted that the amount of charge accumulated in each photosensor may be varied by the readout operation. To solve this problem, the charge accumulating period of each reading operation may be corrected in accordance with an actual charge accumulating period on the basis of the correspondence between the number of times reading operation is performed and the amount of charge accumulated.

As described above, according to the sensitivity setting methods of the above embodiments, sensitivity-adjusting reading operation is executed with respect to a subject image while simultaneously changing the image reading sensitivity stepwise. On the basis of the

distribution of the dynamic ranges of the lightness data obtained at each image reading sensitivity or the linearly differentiated values of the dynamic ranges, an image reading sensitivity which ensures an optimal image reading state is determined easily. This image reading sensitivity (charge accumulating period) can be used as an optimal sensitivity, so that the sensitivity setting is easy. Moreover, since the sensitivity setting processing can be executed using an actual subject, it is not necessary to use a standard sample or the like. Even when the lightness of the subject image varies in response to changes in the environment light, an optimal image reading sensitivity can be set in accordance with the changes in the environmental light. This has eliminated the need to employ a circuit specially designed for sensing the environmental light. Further, even if the photosensors vary in characteristics, the image data obtained from these photosensors is used for determining an optimal sensitivity. Hence, the adverse effects arising from the characteristic variations can be remarkably suppressed.

According to the sensitivity setting method of the fifth embodiment, abnormal values, which deviate from the main change trend of lightness data, are removed from the lightness data, and a row or rows that are in an optimal image reading state are selected in a simple

manner on the basis of the abnormal value-free
lightness data. The image reading sensitivity (charge
accumulating period) set for that specific row section
can be used as an optimal sensitivity. According to
5 the sensitivity setting method of the sixth and seventh
embodiments, only a specific row section of the
photosensor array is used in the sensitivity-adjusting
reading operation. Alternatively, the presence of an
abnormal pixel is determined, and a specific row
10 section that does not contain an abnormal pixel is used
for the sensitivity-adjusting reading operation.
Therefore, the image reading sensitivity can be set at
an optimal value without being adversely affected by an
abnormal pixel, which is due to a foreign substance
15 adhering to the sensing surface of the photosensor
array, a defect of the photosensor element, or the
like.

In each of the embodiments described above, the
sensitivity-adjusting reading operation is executed
20 prior to the normal reading operation. The present
invention is not limited to this. For example, the
sensitivity-adjusting reading operation may be executed
in the standby state, i.e., the state where the
photosensor system is operating but a subject has not
25 yet been placed.

In addition, the sensitivity-adjusting reading
operation was described as being performed whenever the

normal reading operation is executed for a subject image. The present invention is not limited to this. For example, the sensitivity-adjusting reading operation may be performed only when there is a change in the use environment, or when a predetermined length of time has elapsed.

The image reading sensitivity (charge accumulating period) setting method applied to sensitivity setting processing according to the present invention is not limited to the above embodiments. As far as image data of a subject image can be obtained at different reading sensitivities, e.g., a series of processes described in the prior art: reset operation → charge accumulating operation → pre-charge operation → readout operation can be repeated a plurality of number of times at different reading sensitivities, thereby obtaining image data at different reading sensitivities.

Alternatively, any other methods may also be employed.

A description will now be given of the effective voltages of signals which are applied to the top and bottom gate terminals TG and BG in the sensitivity-adjusting reading operation and the image reading operation when the photosensor array of the present invention is made of a double-gate photosensor 10, and of a method for controlling the effective voltage to be an optimal value.

As is apparent from FIGS. 35A to 35H, 36A to 36H,

37A to 37J and 41A to 41C, the top gate terminal TG receives a high-level signal voltage V_{tgh} as a reset pulse only for a very short time (T_{reset}), and a low-level signal voltage V_{tgl} for the remaining relatively long period in sensitivity-adjusting reading operation and image reading operation. In the sensitivity-adjusting reading and image reading periods, the effective voltage applied to the top gate terminal TG greatly shifts to the low-level side. Since an optimal charge accumulating period set for image reading operation is changed and set in accordance with the ambient illuminance or the like if necessary, the effective voltage applied to the top gate terminal TG inevitably varies.

In the sensitivity-adjusting reading operation and the image reading operation, the bottom gate terminal BG receives a high-level signal voltage V_{bgh} only for a very short time (T_{read}), and a low-level signal voltage V_{bgl} for the remaining relatively long period. In the sensitivity-adjusting reading and image reading periods, the effective voltage applied to the bottom gate terminal BG also greatly shifts to the low-level side. Since an optimal charge accumulating period set for image reading operation is changed and set in accordance with the ambient illuminance or the like if necessary, the effective voltage applied to the bottom gate terminal BG inevitably varies.

If such a voltage shifted to a voltage of a specific polarity is kept applied to the gate electrode, the gate electrode traps holes to degrade the element characteristics of the double-gate photosensor and change the sensitivity characteristics.

To prevent this, an effective voltage adjusting period for correcting effective voltages applied to the top and bottom gate terminals TG and BG is set after the sensitivity-adjusting reading and image reading periods. During the effective voltage adjusting period, predetermined correction signals are applied. One of them is for setting an effective voltage applied to the top gate terminal TG to an optimal value V_{te} of the effective voltage of the top gate electrode set in accordance with the sensitivity characteristics of the double-gate photosensor. Another correction signal is for setting an effective voltage applied to the bottom gate terminal BG to an optimal value V_{be} of the effective voltage of the bottom gate electrode. This can suppress changes in sensitivity characteristics caused by degradation in the element characteristics of the photosensor, and can improve the reliability of the photosensor system.

In a photosensor system drive control method according to the present invention, the sensitivity-adjusting reading operation of each embodiment can be performed immediately before the image reading

operation, and the effective voltage adjusting period can be set after the image reading period. Operations of this case will be described with reference to the Figures.

5 FIGS. 38A to 38H are timing charts showing an embodiment wherein the effective voltage adjusting period is set after the sensitivity-adjusting reading and image reading periods.

10 As the drive control method during the sensitivity-adjusting reading period, the drive control method in FIGS. 36A to 36H described above is applied. The same reference numerals denote the same parts, and a description thereof will be omitted. The reset pulses $\phi T1$, $\phi T2$, ..., ϕTn are pulse signals whose high and low levels are signal voltages $Vtgh$ and $Vtgl$,
15 respectively. The readout pulses $\phi B1$, $\phi B2$, ..., ϕBn are pulse signals whose high and low levels are signal voltages $Vbgh$ and $Vbgl$, respectively. As the drive control method during the sensitivity-adjusting reading
20 period, the operation shown in FIGS. 35A to 35H or the operation shown in FIGS. 37A to 37J may be applied. Needless to say, the present invention is not limited to these methods.

25 The drive control method during the image reading period is based on the conventional photosensor system drive control method shown in FIGS. 41A to 41D. To shorten the operation time, photosensors are driven

by overlapping the charge accumulating periods of
respective rows at timings so as not to overlap reset,
pre-charge, and readout pulses. That is, as shown in
FIGS. 38A to 38C, the reset pulses $\phi T1$, $\phi T2$, ..., ϕTn
5 are sequentially applied to the respective top gate
lines 101 connected to the top gate terminals TG of
the double-gate photosensors 10 in the row direction,
thereby starting the reset period T_{reset} , and initial-
izing the double-gate photosensors 10 of respective
10 rows. Similar to the above-described sensitivity-
adjusting reading operation, the reset pulses $\phi T1$,
 $\phi T2$, ..., ϕTn are pulse signals whose high and low
levels are the signal voltages V_{tgh} and V_{tgl} ,
respectively. Except for timings at which the reset
15 pulses $\phi T1$, $\phi T2$, ..., ϕTn of high-level V_{tgh} are
applied, the low-level signal voltage V_{tgl} is applied.

The reset pulses $\phi T1$, $\phi T2$, ..., ϕTn fall to
end the reset period T_{reset} . Then, optimal light
accumulating periods T_a obtained by each embodiment
20 for respective rows based on sensitivity-adjusting
reading operation sequentially start, and charges
(holes) are generated and accumulated in the channel
regions in accordance with light quantities entering
the double-gate photosensors 10 from their top gate
25 electrode side. As shown in FIG. 38G, pre-charge
operation of applying the pre-charge signal ϕ_{pg} to
start the pre-charge period T_{prch} , and applying the

pre-charge voltage V_{prch} to the data line 103 to cause the drain electrode of the double-gate photosensor 10 to hold a predetermined voltage is performed during the light accumulating period T_a . As shown in FIGS. 38D to 38F, the readout pulses $\phi B1$, $\phi B2$, ..., ϕBn are sequentially applied in units of rows to the bottom gate lines 102 of double-gate photosensors 10 in which the optimal light accumulating period T_a and pre-charge period T_{prch} end. Then, the readout period T_{read} starts, and voltage changes V_D corresponding to charges accumulated in the double-gate photosensors 10 are read out from the output circuit section 113 via the data lines 103, as shown in FIG. 38H. Similar to the sensitivity-adjusting reading operation described above, the readout pulses $\phi B1$, $\phi B2$, ..., ϕBn are pulse signals whose high and low levels are at the signal voltages V_{bgh} and V_{bgl} , respectively. Till timings at which the readout pulses $\phi B1$, $\phi B2$, ..., ϕBn of high-level V_{bgh} are applied, the low-level signal voltage V_{bgl} has been applied.

After image reading operation is completed for all the rows, effective voltage adjustment operation of adjusting the shifts of the effective voltages of signals applied to each gate electrode in the sensitivity-adjusting reading and image reading periods and optimizing the effective voltages is executed in the effective voltage adjusting period. More

specifically, as shown in FIGS. 38A to 38C, the top gate line 101 of each row receives a correction signal having a high-level period (T_{tph}) and low-level period (T_{tpl}) so as to attain a predetermined effective voltage capable of adjusting the effective voltage of a signal voltage applied to the top gate line 101, i.e., top gate terminal TG of the double-gate photosensor 10 in response to a reset pulse in the sensitivity-adjusting reading and image reading periods to an optimal value V_{te} set in advance in accordance with the sensitivity characteristics of the double-gate photosensor 10.

Similarly, the bottom gate line 102 of each row receives a correction signal having a high-level period (T_{bph}) and low-level periods (T_{bpla} and T_{bplb}) so as to attain a predetermined effective voltage capable of adjusting the effective voltage of a signal voltage applied to the bottom gate line 102, i.e., bottom gate terminal BG of the double-gate photosensor 10 in response to a readout pulse to an optimal value V_{be} set in advance in accordance with the sensitivity characteristics of the double-gate photosensor 10.

As a result, the effective values of voltages applied to the top and bottom gate terminals TG and BG of the photosensor element can be set to optimal values to suppress changes in sensitivity characteristics caused by degradation in the element characteristics of

the photosensor, and to improve the reliability of the photosensor system.

101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
2235
2236
2237
2238
2239
2240
2241
2242
2243
2244
2245
2246
2247
2248
2249
2250
2251
2252
2253
2254
2255
2256
2257
2258
2259
2260
2261
2262
2263
2264
2265
2266
2267
2268
2269
2270
2271
2272
2273
2274
2275
2276
2277
2278
2279
2280
2281
2282
2283
2284
2285
2286
2287
2288
2289
2290
2291
2292
2293
2294
2295